SCHILLER

CARDIOVIT AT-6

SERVICE MANUAL

General Remarks

The CARDIOVIT AT-6 is constructed modularly. This means that in case of defect, each part, each board is replaced as a complete unit. The defective boards are then repaired by the manufacturer.

The few exceptions from this rule are described in this manual together with the necessary settings and adjustments. This work should only be carried out by competent, authorized technicians. The manufacturer declines any responsibility for inadequate repairs.

Allgemeine Hinweise

Der CARDIOVIT AT-6 ist modular aufgebaut, d.h. jeder Teil, jedes Board wird bei Defekt als ganze Einheit ersetzt. Die fehlerhaften Boards werden dann vom Hersteller repariert.

Die wenigen Ausnahmen von dieser Regel sind im vorliegenden Handbuch zusammen mit den notwendigen Einstell- und Abgleicharbeiten eingehend beschrieben. Diese Arbeiten sollten nur von befähigten, autorisierten Technikern ausgeführt werden. Für unsachgemässe Reparaturen lehnt der Hersteller jede Haftung ab.

SECTION 1

BLOCK SCHEMATIC

Drawing No.

Block Diagram AT-6   -

AT-6 BLOCK

TOP CASE

LCD — ST4 — MICROPROCESSOR — ST3A ⊙ ACC

KEYBOARD — ST5 — CONTRAST

PAPERMARK DETECTOR — ST11 — ST1

TREADMILL

THERMAL PRINTHEAD

PRINTER TIMER — ST10 — ST9 — ST2

BACKPLANE

RS-232 SPIROMETRY VIDEO

ST6

ECG AMPLIFIER — ST7

ST16

SCOPE/DC3

ERGO

DC1

DC2

BEEPER

M STEPPER MOTOR

ST13

ST6

TEST

PATIENT

ST12

POWER SUPPLY

ST8 — ST14 — LINE

BATTERY 12V/1.9A

SECTION 2

MICROPROCESSOR CIRCUITS MK2-1

Keyboard ST3

Keyboard/LED-controller

beeper

motor speed

Program-mable Timer (3*16 bit)

LCD refresh RAM (4 kbyte)

Dynamic RAM (512 kbyte)

LCD controller

ST4 LCD

Interrupt 4

Static RAM (16 kbyte)

μProcessor 68000 (10 MHz)

Power-on Reset

Program memory (EPROM 192/384 kbyte)

Interrupt 2

real time clock calendar

ECG-Amplifier

ECG Interface

8 channel A/D converter

DC inputs

Motor control

on/off

direction

4 channel D/A converter

scope output

EEPROM 64 x 16 bit

Thermal Printer Interface

TPCLK
TPDATA
TPL

Connect to Pull-up Arrays
R21,R23,R29 (7x10k):
 - U25: 2,5,6,10,11,13,14
 - U25: 2,3,5,11,14
 - U27: 2,5,6,10,11,13,14

LCDAS

HC573 U18

A6	2	1D	1Q	19	LLA0
A7	3	2D	2Q	18	LLA1
A8	4	3D	3Q	17	LLA2
A1	5	4D	4Q	16	LMA0
A2	6	5D	5Q	15	LMA1
A3	7	6D	6Q	14	LMA2
A4	8	7D	7Q	13	LMA3
A5	9	8D	8Q	12	LMA4

11 C   OE 1

HC573 U19

A9	2	1D	1Q	19	LMA5
A10	3	2D	2Q	18	LMA6
A11	4	3D	3Q	17	LMA7
A12	5	4D	4Q	16	LMA11
	6	5D	5Q	15	
	7	6D	6Q	14	
	8	7D	7Q	13	
	9	8D	8Q	12	

11 C   OE 1

6264 U20

LLA0	10	A0	O0	11	LD0
LLA1	9	A1	O1	12	LD1
LLA2	8	A2	O2	13	LD2
LMA0	7	A3	O3	15	LD3
LMA1	6	A4	O4	16	LD4
LMA2	5	A5	O5	17	LD5
LMA3	4	A6	O6	18	LD6
LMA4	3	A7	O7	19	LD7
LMA5	25	A8			
LMA6	24	A9			
LMA7	21	A10			
LMA11	23	A11			
	2	A12			

20 CS1
22 OE
27 WE
26 CS2

LCDW

HC573 U21

D0	8	1D	1Q	18	LD0
D1	6	2D	2Q	15	LD1
D2	4	3D	3Q	17	LD2
D3	2	4D	4Q	19	LD3
D4	3	5D	5Q	18	LD4
D5	5	6D	6Q	16	LD5
D6	7	7D	7Q	14	LD6
D7	9	8D	8Q	12	LD7

11 C   OE 1

MSM6240GS U17

LLA0	1	LA0	HS0	49
LLA1	2	LA1	HS1	48
LLA2	3	LA2	HS2	47
	4	LA3	OEEN	53
	5	LA4	XT	52	CLK2
LMA0	6	MA0	XT	51
LMA1	7	MA1	CL	50
LMA2	8	MA2	UDBL	46
LMA3	9	MA3	UDEN	45
LMA4	10	MA4	CHBL	44
LMA5	11	MA5	DAEN	43
LMA6	12	MA6	REN	42
LMA7	13	MA7	CSEN	39
LMA8	14	MA8	DIEN	38
	15	MA9	TEST1	41
	16	MA10	TEST2	40
LMA11	17	MA11	BUSV	37
	18	D0	LIP	36	DCL1
	19	D1	FRP	35	DFLM
	20	D2	FRM	34	DM
	21	D3	CP	33	DCL2
	22	D4	ED1	31
	23	D5	ED2	29
	24	D6	OD1	30	DD1
	26	D7	OD2	28	DD2
	57	S0	MCE	27
	56	S1		
	55	S2		
	54	S3		
	59	CS0		
	58	CS1		

V0

MB673201 U16

D0	51	D0	PA0	4	EKGRES	SID
D1	52	D1	PA1	5	EFTL	SIF
D2	53	D2	PA2	6	PA2
D3	54	D3	PA3	7	PA3	BLOW
D4	55	D4	PA4	8	PA4
D5	56	D5	PA5	9	PA5
D6	59	D6	PA6	11	PA6
D7	60	D7	PA7	12	PA7
D8	61	D8	PA8	13	CHAD0	PMARK
D9	62	D9	PA9	14	CHAD1	MCLK
D10	63	D10	PA10	15	CHAD3
D11	64	D11	PA11	16	TRACK
6A	50	CS	PB0	20	LED0
RXW	49	RXW	PB1	21	LED1
UDS	45	UDS	PB2	22	LED2
LDS	44	LDS	PB3	23	LED3	SOD
A1	48	A1	PB4	24	LED4
A2	47	A2	PB5	27	LED5
A3	46	A3	PB6	28	LED6
	17	CLK	PB7	29	LED7
RES	43	MR	PB8	30	LR0
			PB9	31	LR1
WP0	1	WP0	PB10	32	LR2
WP1	2	WP1	PB11	33	OFF	STSBUS
SIS	37	SIS	BST	34
	36	SIF	FW	35	FW
TPL0	40	IP0	KRE	19
TPL1	39	IP1	KON	3	KONU
TPL2	38	IP2	INT	41
			CK4	18	SIF

INT
A4
CLK1
CLK2
CLK4

HC390 U24

1	1A	1QA	3
2	CLR	1QB	5
4	1B	1QC	6
		1QD	7
15	2A	2QA	11
14	CLR	2QB	13
12	2B	2QC	10
		2QD	9

CLK.2
CLK04

−12V R20 470E P1 5k
R19 4k7

HC04 U15E
9 [8
R4 3.3 M C7 10 pF
Q3 24.000 MHz C8 33 pF

HC259 U22

A5	1	A	Q0	4	TPS
A6	2	B	Q1	5	MON
A7	3	C	Q2	6	SOD
A4	13	Din	Q3	7
			Q4	9
			Q5	10
			Q6	11
			Q7	12
	14	G		
RES	15	CLR		

SOS

59308 U23
CS DO 4
SK
DI

59308 U55
CS DO 4
SK
DI

Connect to pull-up arrays
R21,R29,R30 (7*10k):
− U25: 2,5,6,10,11,13,14
− U26: 2,3,5,11,14
− U27: 2,5,6,10,11,13,14

HC257 U25
2	1A	1Y	4	D0
3	1B			
5	2A	2Y	7	D1
6	2B			
11	3A	3Y	9	D2
10	3B			
14	4A	4Y	12	D3
13	4B			
1	SEL			
15	OE			

HC257 U26
2	1A	1Y	4	D4
3	1B			
5	2A	2Y	7	D5
6	2B			
11	3A	3Y	9	D6
10	3B			
14	4A	4Y	12	D7
13	4B			
1	SEL			
15	OE			

HC257 U27
2	1A	1Y	4	D8
3	1B			
5	2A	2Y	7	D9
6	2B			
11	3A	3Y	9	D10
10	3B			
14	4A	4Y	12	D11
13	4B			
1	SEL			
15	OE			

KBIN0 KBIN1 KBIN2 KBIN3
KBIN7 KBIN6 KBIN5 KBIN4
KBIN8 KBIN9 KBIN10 KBIN11

R6 10k R31 100k R32 100k R34 100k R33 100k

FW
FF
SOF
BAT
IN1

CBUS
IOBUS

SCHILLER AG, CH-6340 BAAR
ALIGASSE 68

TITLE: MICROCOMPUTER MK2-1 LCD CONTROLLER

SIZE B CODE NUMBER 1200101 D2 REJ A

DATE 18 JUNE 1986 SHEET

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE PROCESSOR CARD HK2-1/C
MEMORY

SIZE	CODE	NUMBER	REV
B		1100101 D3	A

DATE 29 SEPTEMBER 85 SHEET

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE: PROCESSOR CARD MK2-L/C MEMORY

SIZE: B | CODE | NUMBER 1200101 D3 | REV A

DATE 29 SEPTEMBER 86 | FILE: MK2\MK21MEM

U36 HM4256
U37 HM4256
U38 HM4256
U39 HM4256
U41 HM4256
U42 HM4256
U43 HM4256
U44 HM4256

VCC   Pin 10
GND   Pin 20
NC   PIN 5   at GND

SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			
TITLE	PROCESSOR CARD MK2-1/D MEMORY 2		
SIZE	CODE	NUMBER	REV
		1200101	B
DATE	19. June 1989	File:MK2/MEMORV2	

DAC8408GP

D0 9 DB0 VrA 3
D1 10 DB1 RFA 8
D2 11 DB2 O1A 4
D3 12 DB3 O2A 5
D4 13 DB4 VrB 6
D5 14 DB5 RFB 7
D6 15 DB6 O1B 6
D7 16 DB7 VrC 27
DS1 19 DS1 RFC 26
DS2 20 DS2 O1C 25
EXW 18 R/W O2C 24
W1 17 A/B VrD 21
RFD 22
O1D 23
US4

CBUS

C12 3n9
C14 3n9
C11 33n
C16 3n9
C18 33p

US6A TL064
US6C TL064
US7A TL064
US7B TL064

R7 15k0
R10 15k0
R13 15k0
R16 15k0

R8 30k0
R9 15k0
C13 10n
US6B TL064 ES0

R11 30k0
R12 15k0
C15 10n
US6D TL064 ES1

R14 30k0
R15 15k0
C17 10n
US7C TL064 ES2

R18 15k0
C19 33p
US7D TL064 ERGOP

+12V
R6 10k
US8B TL062
US8A TL062

LM336B 5.0 V D1
C9 33n
C46 2.2uF
C10 33n
C20 33n

+12V
C24 33 uF
C21 33 nF
C26 68 uF
C23 33 nF
C25 33 uF
C22 33 nF
-12V

IOBUS

ADC0809

D0 17 D0 REF+ 12
D1 14 D1 VCC 11
D2 15 D2 REF- 16
D3 8 D3
D4 18 D4 IN0 26 ERPM
D5 19 D5 IN1 27 DC4
D6 20 D6 IN2 28 DC2
D7 21 D7 IN3 1 P2.5V
A1 25 A0 IN4 2 ERGON
A2 24 A1 IN5 3 A15
A3 23 A2 IN6 4 DC3
ADCP 22 ALE IN7 5 DC1
6 ST
9 OE
CLK1 10 CLK
7 EOC
US9

ES0
ES1
ES2
ER50P

C13 10n   R9 15k0
R8 30k0
TL064
U55B
C15 10n   R12 15k0
R11 30k0
TL064
U56D
C17 10n   R15 15k0
R14 30k0
TL064
U57C
C19 33p   R18 15k0
TL064
U57D

C21 33 nF
C23 33 nF
C22 33 nF
C24 33 uF
C26 6,8 uF
C25 33 uF
+12V
-12V

R7 15k0
TL064
U56A
R10 15k0
TL064
U56C
R13 16k0
TL064
U57A
R16 15k0
TL064
U57B

C12 3n9
C14 3n9
C16 3n3
C13 33p
C11 33n

C10 33n
TL062
U58B
TL062
U58A
C46 2.2uF
C20 33n
IORUS

+12V
R6 10k
C9 33n
LM336B 5.0 V
D1
ADC0803
REF+
VCC
REF-
IN0
IN1
IN2
IN3
IN4
IN5
IN6
IN7
ALE
ST
OE
CLK
EOC
U59
CLK1

ERPM
DC4
DC2
P2.5V
ER50W
AT5
DC3
DC1
ADCP

DAC8408GP
DB0 VrA
DB1 RFA
DB2 O1A
DB3 O2A
DB4 VrB
DB5 RFB
DB6 O1B
DB7 O2B
DS1 RFC
DS2 O1C
R/W O2C
A/B VrD
RFD
O1D
U54

D0
D1
D2
D3
D4
D5
D6
D7
DS1
DS2
RXW
A1

CBUS

Pin	Signal
1A	D0
1C	D8
2A	D1
2C	D9
3A	D2
3C	D10
4A	D3
4C	D11
5A	D4
5C	D12
6A	D5
6C	D13
7A	D6
7C	D14
8A	D7
8C	D15
9A	GND
9C	GND
10A	+12V
10C	ASO
11A	GND
11C	AS1
12A	UOE/
12C	NC
13A	LOE/
13C	PER2
14A	LWE/
14C	RESET
15A	GND
15C	A23
16A	UWE/
16C	A22
17A	WRITE
17C	A21
18A	AS
18C	A20
19A	PER1/
19C	A19
20A	INT/
20C	A18
21A	CS/
21C	A17
22A	CLK2
22C	A16
23A	C8/
23C	A15
24A	A7
24C	A14
25A	A6
25C	A13
26A	A5
26C	A12
27A	A4
27C	A11
28A	A3
28C	A10
29A	A2
29C	A9
30A	A1
30C	A8
31A	C7/
31C	-12V
32A	+5V
32C	+5V

ST 1

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE: MICROCOMPUTER MK2-1
TP CONTROLLER

SIZE	CODE	NUMBER	REV
B		1100101 D5	A

DATE: 18 JUNE 1986   SHEET:

1A		D0
1C		D8
2A		D1
2C		D9
3A		D2
3C		D10
4A		D3
4C		D11
5A		D4
5C		D12
6A		D5
6C		D13
7A		D6
7C		D14
8A		D7
8C		D15
9A		GND
9C		GND
10A		+12V
10C		AS0
11A		GND
11C		AS1
12A		UOE/
12C		NC
13A		LOE/
13C		PER2
14A		LWE/
14C		RESET
15A		GND
15C		A23
16A		UWE/
16C		A22
17A		WRITE
17C		A21
18A		AS
18C		A20
19A		PER1/
19C		A19
20A		INT/
20C		A18
21A		C5/
21C		A17
22A		CLK2
22C		A16
23A		C6/
23C		A15
24A		A7
24C		A14
25A		A6
25C		A13
26A		A5
26C		A12
27A		A4
27C		A11
28A		A3
28C		A10
29A		A2
29C		A9
30A		A1
30C		A8
31A		C7/
31C		-12V
32A		+5V
32C		+5V

ST 1

Pin	Signal
1A	CHAD0
1C	UP0
2A	CHAD1
2C	WP1
3A	TRACK
3C	EFIL
4A	CHADB
4C	CLK.2
5A	EKGRE
5C	KONV
6A	UPOFF
6C	GND
7A	AI0
7C	AI4
8A	GND
8C	GND
9A	AI1
9C	AI5
10A	GND
10C	GND
11A	AI2
11C	AI6
12A	GND
12C	GND
13A	AI3
13C	AI7
14A	GND
14C	GND
15A	ERGOP
15C	PA3
16A	GND
16C	GND
17A	SP
17C	EP
18A	GND
18C	GND
19A	ES0
19C	PA5
20A	ES1
20C	PA6
21A	ES2
21C	PA7
22A	GND
22C	GND
23A	TPC
23C	TPD
24A	GND
24C	GND
25A	IN1
25C	TPS
26A	+12V
26C	+12V
27A	BLOW
27C	FMARK
28A	MCLK
28C	BATT
29A	PA2
29C	MON
30A	GND
30C	GND
31A	-12V
31C	-12V
32A	+5V
32C	+5V

ST 2

Pin	Signal
1A	CHAD0
1C	WP0
2A	CHAD1
2C	WP1
3A	TRACK
3C	EFIL
4A	CHAD3
4C	CLK.2
5A	EKGRE
5C	KONV
6A	UPOFF
6C	GND
7A	AI0
7C	AI4
8A	GND
8C	GND
9A	AI1
9C	AI5
10A	GND
10C	GND
11A	AI2
11C	AI6
12A	GND
12C	GND
13A	AI3
13C	AI7
14A	GND
14C	GND
15A	ERGOP
15C	PA3
16A	GND
16C	GND
17A	SP
17C	SP
18A	GND
18C	GND
19A	ES0
19C	PA5
20A	ES1
20C	PA6
21A	ES2
21C	PA7
22A	GND
22C	GND
23A	TPC
23C	TPD
24A	GND
24C	GND
25A	IN1
25C	TPS
26A	+12V
26C	+12V
27A	BLOW
27C	PMARK
28A	MCLK
28C	BATT
29A	PA2
29C	MON
30A	GND
30C	GND
31A	−12V
31C	−12V
32A	+5V
32C	+5V

ST 2

$\overline{SIF}$ ——▷— 6

$\overline{SIS}$ ——▷— 4

SID ——▷— 1

SOD ——▷— 3   ST 3

$\overline{SOS}$ ——▷— 5

SOF ——▷— 7

GND ——▷— 2

▽

SOD ——▷— 1

SID ——▷— 2   ST 3A
                    AT 6
GND ——▷— 3

▽

ST 4
----

	a	b
1	DD1	DFLM
2	DM	DCL1
3	DCL2	DD2
4	+5V	GND
5	-12V	VO

$\overline{SIF}$ ▶ 6

$\overline{SIS}$ ▶ 4

SID ▶ 1

SOD ▶ 3   ST 3

$\overline{SOS}$ ▶ 5

SOF ▶ 7

GND ▶ 2

▽

SOD ▶ 1

SID ▶ 2   ST 3A
AT 6

GND ▶ 3

▽

ST 4

	a	b
1	DD1	DFLM
2	DM	DCL1
3	DCL2	DD2
4	+5V	GND
5	-12V	VO

SCHILLER AG, CH-6340 BAAR		
ALTGASSE 68		

TITLE	PINBELEGUNG ST 3(A)/ST 4	
	PINOUT MK2-1C	

SIZE	CODE	NUMBER	REV
B		1200101 D8	A

DATE	9. OKT. 1986	SHEET

SCHILLER AG, CH-6340 BAAR				
ALTGASSE 68				
TITLE				
DISPOSITION MK2-1C				
SIZE	CODE	NUMBER		REV
B			1100103	A
DATE 30 APRIL 1986			SHEET	

ST 5

ST 8

S LED's

ST 5

	a	b
1	KBIN11	KBIN10
2	KBIN9	KBIN8
3	LEDROW1	LEDROW0
4	LEDROW2	LED0
5	LED2	LED1
6	LED4	LED3
7	LED7	LED5
8	KBIN6	LED6
9	KBIN5	KBIN7
10	KBIN3	KBIN4
11	KBIN1	KBIN2
12	KBIN0	+5V
13	LEDROW3	GND

ST 5

	a	b
1	KBIN11	KBIN10
2	KBIN9	KBIN8
3	LEDROW1	LEDROW0
4	LEDROW2	LED0
5	LED2	LED1
6	LED4	LED3
7	LED7	LED5
8	KBIN6	LED6
9	KBIN5	KBIN7
10	KBIN3	KBIN4
11	KBIN1	KBIN2
12	KBIN0	+5U
13	LEDROW3	GND

Bank 1
Bank 2

SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			
TITLE	MICROCOMPUTER MK2-1E		
	DISPOSITION		
SIZE	CODE	NUMBER	REV
B			A
DATE	16.JUNE 1989	FILE:	

262144-word x 4-bit CMOS Dynamic Random Access Memory   *128 kbit /chip.*

The Hitachi HM514256 Series is a CMOS dynamic RAM organized 262144-word x 4-bit. HM514256 has realized higher density, higher performance and various functions by employing 1.3 μm CMOS process technology and some new CMOS circuit design technologies. The HM514256 offers Page Mode as a high speed access mode.

Multiplexed address input permits the HM514256 to be packaged in standard 20-pin plastic DIP, 20-pin plastic SOJ and 20-pin plastic ZIP.

Features
- High Speed ..... Access Time 100/120/150 ns (max)
- Lower Power .... Active 300 mW, Standby 11mW
- Single 5V (±10%)
- Page Mode
- 512 refresh cycle .... 8 ms
- 2 variations of refresh .... $\overline{RAS}$ only refresh
  $\overline{CAS}$ before $\overline{RAS}$ refresh

Ordering Information

Type No.	Access Time	Package
HM514256P-10	100 ns	
HM514256P-12	120ns	300 mil 20 pin Plastic DIP
HM514256P-15	150ns	
HM514256ZP-10	100ns	
HM514256ZP-12	120ns	20 pin Plastic ZIP
HM514256ZP-15	150ns	
HM514256JP-10	100ns	
HM514256JP-12	120ns	20 pin Plastic SOJ
HM514256JP-15	150ns	

HM514256P Series
(DP-20NA)

HM514256ZP Series
(ZP-20)

HM514256JP Series
(CP-20D)

Pin Description

A0 – A8	Address Inputs
$\overline{CAS}$	Column Address Strobe
I/O – I/O4	Data In/Data Out
$\overline{OE}$	Output Enable
$\overline{RAS}$	Row Address Strobe
$\overline{WE}$	Read/Write Input
V_{CC}	Power (+5V)
V_{SS}	Ground
A0 – A8	Refresh Address Input

Note) The specifications of this device are subject to change without notice. Please contact your nearest Hitachi's Sales Dept. regarding specifications.

Pin Arrangement

HM514256P Series (Top View)

HM514256JP Series (Top View)

HM514256ZP Series (Bottom View)

Block Diagram

Absolute Maximum Ratings

Voltage on any pin relative to V_{SS}	-1V to +7V
Operating temperature, Ta (Ambient)	0°C to +70°C
Storage temperature (Ambient)	-55°C to +125°C
Power dissipation	1 W
Short circuit output current	50 mA

Recommended DC Operating Conditions (Ta = 0 to +70°C)

Parameter	Symbol	Min	Typ	Max	Unit
Supply voltage	V_{CC}	4.5	5.0	5.5	V
Input High voltage	V_{IH}	2.4	–	6.5	V
Input Low voltage	V_{IL}	-2.0	–	0.8	V

Note) All voltages referenced to V_{SS}.

DC Electrical Characteristics (Ta = 0 to +70°C, V_{CC} = 5V ± 10%, V_{SS} = 0V)

Parameter	Symbol	Min	Max	Unit	Notes
Operating current t_{RC} = 260 ns t_{RC} = 220 ns t_{RC} = 190 ns	I_{CC1}	–	40 47 55	mA	*1, *4
Standby current	I_{CC2}	– –	2 1	mA mA	TTL Interface CMOS Interface
Refresh current t_{RC} = 260 ns t_{RC} = 220 ns t_{RC} = 190 ns	I_{CC3}	–	40 47 55	mA	$\overline{RAS}$ only Refresh *1
Standby current (Dout Enable) $\overline{RAS}$ = V_{IH}, $\overline{CAS}$ = V_{IL}	I_{CC5}	–	5	mA	*1
Refresh current t_{RC} = 260 ns t_{RC} = 220 ns t_{RC} = 190 ns	I_{CC6}	–	40 47 55	mA	$\overline{CAS}$ before $\overline{RAS}$ Refresh
Operating current t_{RC} = 105 ns t_{RC} = 85 ns t_{RC} = 70 ns	I_{CC7}	–	40 47 55	mA	*1, *5 Page mode
Input leakage 0 < Vin < 7V	I_{LI}	–10	10	μA	
Output leakage 0 < Vout < 7V	I_{LO}	–10	10	μA	Dout is disabled
Output levels High Iout = –5 mA	V_{OH}	2.4	V_{CC}	V	
Low Iout = 4.2 mA	V_{OL}	0	0.4	V	

Capacitance

Parameter	Symbol	Typ	Max	Unit	Notes
Address	C_{I1}	–	5	pF	*2
$\overline{RAS}$, $\overline{CAS}$, $\overline{WE}$, $\overline{OE}$	C_{I2}	–	7	pF	*2
Data-In/Data-Out	$C_{I/O}$	–	10	pF	*2, *3

Notes) *1. I_{CC} depends on output loading condition when the device is selected. I_{CC} max is specified at the output open condition.
*2. Capacitance measured with Boonton Meter or effective capacitance measuring method.
*3. $\overline{CAS}$ = V_{IH} to disable Dout.
*4. Address can be changed less than 3 times while $\overline{RAS}$ is V_{IL}.
*5. Address can be changed once or less while $\overline{CAS}$ = V_{IH}.

Electrical Characteristics and Recommended AC Operating Conditions
(Ta = 0 to +70°C, V_{CC} = 5V ± 10%) *1, *10, *11

Parameter	Symbol	HM514256-10 min	HM514256-10 max	HM514256-12 min	HM514256-12 max	HM514256-15 min	HM514256-15 max	Unit	Notes
Access Time from $\overline{RAS}$	t_{RAC}	–	100	–	120	–	150	ns	*2, *3
Access Time from $\overline{CAS}$	t_{CAC}	–	50	–	60	–	75	ns	*3, *4
Output Buffer Turn-off Delay	t_{OFF1}	–	25	–	30	–	40	ns	*5
Output Buffer Turn-off Delay referenced to $\overline{OE}$	t_{OFF2}	–	25	–	30	–	40	ns	*5
Transition Time (Rise and Fall)	t_T	3	50	3	50	3	50	ns	*6
Random Read or Write Cycle Time	t_{RC}	190	–	220	–	260	–	ns	
$\overline{RAS}$ Precharge Time	t_{RP}	80	–	90	–	100	–	ns	

(to be continued)

⊛ HITACHI

Parameter	Symbol	HM514256-10 min	HM514256-10 max	HM514256-12 min	HM514256-12 max	HM514256-15 min	HM514256-15 max	Unit
$\overline{RAS}$ Pulse Width	t_{RAS}	100	10000	120	10000	150	10000	ns
$\overline{CAS}$ Pulse Width	t_{CAS}	50	10000	60	10000	75	10000	ns
$\overline{RAS}$ to $\overline{CAS}$ Delay Time	t_{RCD}	25	50	25	60	30	75	ns
$\overline{RAS}$ Hold Time	t_{RSH}	50	–	60	–	75	–	ns
$\overline{CAS}$ Hold Time	t_{CSH}	100	–	120	–	150	–	ns
$\overline{CAS}$ to $\overline{RAS}$ Precharge Time	t_{CRP}	10	–	10	–	10	–	ns
Row Address Setup Time	t_{ASR}	0	–	0	–	0	–	ns
Row Address Hold Time	t_{RAH}	15	–	15	–	20	–	ns
Column Address Setup Time	t_{ASC}	0	–	0	–	0	–	ns
Column Address Hold Time	t_{CAH}	20	–	20	–	25	–	ns
Write Command Setup Time	t_{WCS}	0	–	0	–	0	–	ns
Write Command Hold Time	t_{WCH}	20	–	25	–	30	–	ns
Write Command Pulse Width	t_{WP}	15	–	20	–	25	–	ns
Write Command to $\overline{RAS}$ Lead Time	t_{RWL}	35	–	40	–	45	–	ns
Write Command to $\overline{CAS}$ Lead Time	t_{CWL}	35	–	40	–	45	–	ns
Data-in Setup Time	t_{DS}	0	–	0	–	0	–	ns
Data-in Hold Time	t_{DH}	20	–	25	–	30	–	ns
Read Command Setup Time	t_{RCS}	0	–	0	–	0	–	ns
Read Command Hold Time referenced to $\overline{CAS}$	t_{RCH}	0	–	0	–	0	–	ns
Read Command Hold Time referenced to $\overline{RAS}$	t_{RRH}	10	–	10	–	10	–	ns
Refresh Period	t_{REF}	–	8	–	8	–	8	ms
Read-Write Cycle Time	t_{RWC}	265	–	305	–	360	–	ns
Read Modify Write Cycle Time	t_{RWS}	175	–	205	–	250	–	ns
$\overline{RAS}$ to $\overline{WE}$ Delay	t_{RWD}	135	–	160	–	200	–	ns
$\overline{CAS}$ to $\overline{WE}$ Delay	t_{CWD}	85	–	100	–	125	–	ns
$\overline{CAS}$ Setup Time	t_{CSR}	10	–	10	–	10	–	ns
$\overline{CAS}$ Hold Time ($\overline{CAS}$ before $\overline{RAS}$ Refresh)	t_{CHR}	20	–	25	–	30	–	ns
$\overline{RAS}$ Precharge to $\overline{CAS}$ Hold Time	t_{RPC}	10	–	10	–	10	–	ns
Page Mode Read or Write Cycle	t_{PC}	70	–	85	–	105	–	ns
$\overline{CAS}$ Precharge Time, Page Cycle	t_{CP}	10	–	15	–	20	–	ns
Page Mode Read Modify Write Cycle	t_{PCM}	145	–	170	–	205	–	ns
Page Mode $\overline{CAS}$ Pulse Width (Read Modify Write Cycle)	t_{CRW}	125	–	145	–	175	–	ns
Access Time from $\overline{OE}$	t_{OAC}	–	25	–	30	–	40	ns
$\overline{OE}$ to Data-in Delay Time	t_{ODD}	25	–	30	–	40	–	ns
$\overline{CAS}$ to Data-in Delay Time	t_{CDD}	25	–	30	–	40	–	ns
$\overline{OE}$ Hold Time reference to Write	t_{OEH}	25	–	30	–	35	–	ns
$\overline{OE}$ Delay Time from Din	t_{DZO}	0	–	0	–	0	–	ns
$\overline{CAS}$ Delay Time from Din	t_{DZC}	0	–	0	–	0	–	ns

Notes) *1. AC measurements assume t_T = 5 ns.
*2. Assumes that t_{RCD} ≤ t_{RCD} (max). If t_{RCD} is greater than the maximum recommended value shown table, t_{RAC} exceeds the value shown.
*3. Measured with a load circuit equivalent to 2TTL loads and 100pF.
*4. Assumes that t_{RCD} ≥ t_{RCD} (max).
*5. t_{OFF} (max) defines the time at which the output achieves the open circuit condition and is not refe output voltage levels.
*6. V_{IH} (min) and V_{IL} (max) are reference levels for measuring timing of input signals. Also, transition measured between V_{IH} and V_{IL}.
*7. Operation with the t_{RCD} (max) limit insures that t_{RAC} (max) can be met, t_{RCD} (max) is specified ence point only, if t_{RCD} is greater than the specified t_{RCD} (max) limit, then access time is controll sively be t_{CAC}.
*8. t_{WCS} and t_{CWD} are not restrictive operating parameters. They are included in the data sheet as electric teristics only; if t_{WCS} ≥ t_{WCS} (min), the cycle is an early write cycle and the data out pin will rem circuit (high impedance) throughout the entire cycle; if t_{CWD} ≥ t_{CWD} (min), the cycle is a read/writ data output will contain data read from the selected cell; if neither of the above sets of conditions is the condition of the data out (at access time) is indeterminate.
*9. These parameters are referenced to $\overline{CAS}$ leading edge in early write cycles and to $\overline{WE}$ leading edge i write or read-modify-write cycles.
*10. An initial pause of 100μs is required after power-up. Then execute at least 8 initialization cycles.
*11. In delayed write or read-modify-write cycles, $\overline{OE}$ must disable output buffers prior to applying da device.

⊛ HITACHI

HM514256 Series ——————— Preliminary

262144-word x 4-bit CMOS Dynamic Random Access Memory

The Hitachi HM514256 Series is a CMOS dynamic RAM organized 262144-word x 4-bit. HM514256 has realized higher density, higher performance and various functions by employing 1.3 μm CMOS process technology and some new CMOS circuit design technologies. The HM514256 offers Page Mode as a high speed access mode.

Multiplexed address input permits the HM514256 to be packaged in standard 20-pin plastic DIP, 20-pin plastic SOJ and 20-pin plastic ZIP.

Features
● High Speed ..... Access Time 100/120/150 ns (max)
● Lower Power .... Active 300 mW, Standby 11mW
● Single 5V (±10%)
● Page Mode
● 512 refresh cycle .... 8 ms
● 2 variations of refresh .... $\overline{RAS}$ only refresh
  $\overline{CAS}$ before $\overline{RAS}$ refresh

Ordering Information

Type No.	Access Time	Package
HM514256P-10	100 ns	
HM514256P-12	120ns	300 mil 20 pin Plastic DIP
HM514256P-15	150ns	
HM514256ZP-10	100ns	
HM514256ZP-12	120ns	20 pin Plastic ZIP
HM514256ZP-15	150ns	
HM514256JP-10	100ns	
HM514256JP-12	120ns	20 pin Plastic SOJ
HM514256JP-15	150ns	

Pin Arrangement

HM514256P Series

(Top View)

HM514256JP Series

(Top View)

HM514256ZP Series

(Bottom View)

HM514256P Series

(DP-20NA)

HM514256ZP Series

(ZP-20)

HM514256JP Series

(CP-20D)

Pin Description

A0 – A8	Address Inputs
$\overline{CAS}$	Column Address Strobe
I/O – I/O4	Data In/Data Out
$\overline{OE}$	Output Enable
$\overline{RAS}$	Row Address Strobe
$\overline{WE}$	Read/Write Input
V_{CC}	Power (+5V)
V_{SS}	Ground
A0 – A8	Refresh Address Input

Note) The specifications of this device are subject to change without notice. Please contact your nearest Hitachi's Sales Dept. regarding specifications.

Block Diagram

Absolute Maximum Rating

Voltage on any pin relative
Operating temperature, Ta
Storage temperature (Amb
Power dissipation ......
Short circuit output curren

Recommended DC Operati

Parameter	Sy
Supply voltage	
Input High voltage	
Input Low voltage	

Note) All voltages referenced t

◎ HITACHI

SECTION 3

PRINTER TIMER / MOTOR CONTROL / PAPER MARK DETECTOR CIRCUITS
MK2-4 / MK2-5 / MK2-6

MOTOR CONTROL

STEPPER MOTOR

ST 13

+15V
T1
R55 0.1E
T2

C34 470uF

L293
+POW
OUT
INH1 OUT
A OUT
B INH2 OUT
C S2
D S1
U7

R59 1E
R58 1E
R57 1E
R56 1E

RS4 10K

SB150 D20
SB150 D19
SB150 D18
SB150 D17

SB150 D24
SB150 D23
SB150 D22
SB150 D21

L297
SEN2
SEN1
Vref INH1
A
B
C
CLK INH2
RES ENAB
U6

+5V

R53 10K
R52 10K
R51 10K
R50 10K

C20 150nF

CLOCK

MOTOR ON/OFF

ST 6

C35 5.6nF

C36 10uF

R49 100K
R48 2K
R47 1K

SCHILLER AG, CH-6349 BAAR
ALTGASSE 68

TITLE PRINTER TIMER HXZ-5

SIZE	CODE	NUMBER	REV
B		1100501	A

DATE 30 SEPT. 1985   SHEET

IC2	
IC1	ST 10

TITLE PRINTER TIMER   MK2-5
DISPOSITION

SIZE	CODE	NUMBER		REV
B			1100503	A

DATE 30.SEPT. 1986   SHEET

R1 1K
TR1 50K
R2 1K
R3 10K
R4 3K
R5 2K
R6 10K
R7 470K
R8 10E
R9 10K
C1 1nF
C2 100uF
U1 LF311
PS1 SFH900
P1
P2
P3
+5V
PMARK

ST 11

			REV
SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			

TITLE	BACKPLANE MK2-4 PD		
	PAPERMARK DETECTOR		

SIZE	CODE	NUMBER		REV
B		1100401 C3		A

DATE	21.MAI	1986	SHEET

ST16
ST15
ST 7
ST 2
ST11
R5
R6
R1
R3
R4
R2
TR1
C1
U1
ST 6
ST 9
C2
R7
R8
R9
ST 1

ST 6

ST 12
ST 8
ST 14   grün   P20
        rot   P21
        blau   P23
        braun P22
ST 13

P1   P15 P19   P15 P14
     P16 P17
N3   R1 VDR250V
R2 NTC

P10   P8
P29
P34
P35 GND

C52 6800µF
C51 6800µF
C50 6800µF

GL1: 4x JB330
S12/P120A
R55
T2

C1 2200µF 40V
C2 150nF
C3 150nF
L4 300µH
8x SB150D

DU6 L297
C34 470µF
L3 500µH
2x470µF
C10
L2 SB150
T1 RFP6 P08
C6 330p
R47 220E   D36 LL4148 27E   R9F

L297

C55 100µF
C56 470µF
C57 470µF
L5 400µH
L10 300µH
C72 470µF
C73 330p
L11 800µH
T48 RFP6 P08
C82 2x470µF
U11
R90 27E   R82 S.2k
75C 427

C26 2x470µF
C27
L4 300µH
T2 BU571A
T3 RFP6 P08

C43 10µ
C42 10µ

ST 15
GND P28
P24
C9
C10 2x470µF
U11
C15 10µF
C13
R9 500E
R17 0.12E
D5 1N4007   LM336
D4
D7 BAV99
C22

D33 1N5339
R26 T4H BC817
T13
T42 2SA1A 27E

ST 13   P32 P33 P30 P31

SECTION 4

ECG AMPLIFIER CIRCUIT MK1-2

C1
C2
C2
C4
C5
C6
RA
LA
LL (F)
RL (RF)

Patientenkabel

Defibrillationsschutz

Eingangsschutz-Filter

Differential-Verstärker AC-Kupplung / Reset

RL Treiber

CMR

MUX

PWM

ST 7

c1
c2
c5
a1
a2
a3
a4
a5

Gain

Test Buchse
Patientenkabel-Test
Isolation

800V

±5Vi
±2Vref
±9V1

Ref.Spannung

a,c31/-5V
a,c 32/+5V
c4/200kHz

DC 1
DC 2
DC3

Scope-Ausgang

c 13
a 11
a 9

a 19/ch1
a 21/ch3
a 20/ch2

ST 7

3 × F 0.1 A

Stück Nbr. de pieces		Gegenstand Spécification	Pos. Rep.	Material Matière		Modell Modèle	Bemerkungen Observations
II	I	Änderungen: Modifications:				Ersetzt durch Remplacé par	
						Ersatz für Remplace	
					Maßstab Echelle	Gezeichnet Dessiné	
		EKG - VERSTAEKER				Geprüft Contrôle	
		MK1 - 2A					
						Gesehen Vu	
		SCHILLER Switzerland Schiller AG Altgasse 6B CH-6340 Baar Telephone 042/31 53 31 Telex 865140 sbe ch Telefax 042/31 08 80				1100200 a	

ST?

PART B

PART A

PART C

G
C2-F
E
C3-F
D
C4-F
C
C5-F
H
C1-F
B
C6-F
A
LA-F
I
RA-F
K

la1
ra1
s2
s1

P1
P6
P2
P3
P4
P12
P5
P18
P9
P11
P14

PATIENT CABLE

C2
C3
C4
C5
C1
C6
LA
RA
F (LL)
RF (RL)

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE EKG AMPLIFIER MK1-2A

SIZE CODE NUMBER
B   1100201 A1

DATE 25.SEPT. 1986   SHEET

REV
A

ST7

PART B

PART A

PART C

G
C2-F
E
C3-F
D
C4-F
C
C5-F
H
C1-F
B
C6-F
A
LA-F
I
RA-F
K

la1
ra1
s2
s1

P1
P6
P2
P3
P4
P12
P5
P10
P9
P11
P14

PATIENT CABLE

C2
C3
C4
C5
C1
C6
LA
RA
F (LL)
RF (RL)

SCHILLER AG, CH-6340 BAAR
ALTGASSE 63

TITLE   EKG AMPLIFIER MK1-2A

SIZE	CODE	NUMBER	REV
B		1100201 A1	A

DATE 25.SEPT. 1986   SHEET

C2
C3
C4
C5
C1
C6
LA
RA
F (LL)
RF (RL)

PATIENT CABLE

P1
P6
P2
P3
P4
P12
P5
P10
P9
P11
P14

PART A

PART B

ST7

G
C2-F
E
C3-F
D
C4-F
C
C5-F
H
C1-F
B
C6-F
A
LA-F
I
RA-F
K

s1   s2   ra1   la1

PART C

SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			
TITLE	EKG AMPLIFIER MK1-2D		
SIZE	CODE	NUMBER	REV
B		1200201 A1	A
DATE	3.JAN.1990	FILE:MK1\M12DAMF1	

(C2) P1
(Screen) P6
(C3) P2
(C4) P3
(C5) P4
(C1) P12
(C6) P5
(LA) P10
(RA) P9

+2Vi
-2Vi

D9
D3

R8 15k
R12 30k
C3 390pF
C12 120pF

R49 30k
R41 1.1k
R53 15k
R30 39k
R21 3.9k

C31 220nF
C23 150nF

R66 7M5
R66 7M5

T18 2N4393
R106 1.5M

R98 1.1k
C47 150nF
IC4 TL064
C39 3.9nF
R90 47k
R74 2k
R82 160E

s1
s2
ral lal
rel lel

G
E   C3-F
D   C4-F
C   C5-F
H   C1-F
B   C6-F
A   LA-F
I   RA-F
K

C2-F

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE EKG AMPLIFIER MK1-2F
PART A

SIZE	CODE NUMBER	REV
B	1100201 A2	A

DATE 4 JULI 1996

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE EKG AMPLIFIER MK1-2A PART B

SIZE	CODE	NUMBER	REV
B		1100201 A3	A

DATE 25.SEPT. 1986 | SHEET

ST7

+5U h6 MP0   R124 5.1k
+5U b5 MP1   R125 5.1k
+5U b3 KONU   R137 1.3k
+5U b10 CHAD0 R133 1.3k
+5U b9 CHAD1 R134 1.3k
+5U b4 TRACK R135 1.3k
+5U b8 CHAD3 R136 1.3k
+5U b7 EKGRES R138 2.7k   GND

OP1 PC900
OP2 PC900
OP8 PC900
OP0 PC900
OP5 PC900
OP6 PC900
OP7 PC900
OP3 PC817

+5Ui
C135 680pF

R139 30k
-9Ui

Vx   R245 1.1k   C135 47uF
-5Ui

R126 15k
R127 15k
R128 15k
R129 15k

D5 MMBD914 R122 1.3k C61 3.9nF
D6 MMBD914 R123 1.3k C52 3.9nF

R130 7.5k R246 2.7k

IC13 TL084
IC13 TL084
IC13 TL084

R131 15K
1.25V LM385 b1
C65 1uF
R232 10R
R142 20K
C66 1.5nF

T24 J270 -2.5Ui

R121 1.1K
R119 1.1K
R118 1.1K
R120 1.1K

TL 084 PIN 4 +5Ui
        PIN 11 -5Ui

IC15 HEF4051 -5Ui
UDD INH VEE VSS
4IO 7IO 6IO 5IO 4IO 3IO 2IO 1IO 0IO CBA
+5Ui RA-F C1-F C3-F C5-F I H M Q

IC16 HEF4051 -5Ui
UDD INH VEE VSS
4IO 7IO 6IO 5IO 4IO 3IO 2IO 1IO 0IO CBA
+5Ui LA-F C2-F C4-F C6-F A G S U

R117 150k
T10 BC847
R116 47k
+5Ui -5Ui

TL 064 PIN 4 +5Ui
        PIN 11 -5Ui

IC7 TL064   C2-F
IC7 TL064   C3-F   C60
IC7 TL064   C4-F   C59
IC7 TL064   C5-F   C57
IC6 TL064   C1-F   C54
IC6 TL064   C6-F   C56
IC5 TL064   LA-F   C55
IC6 TL064   RA-F   C53

C58 15nF

IC18 HEF4066
IC17 HEF4066

MC14551 IC19
-1.5V E W1
 -5V Vee
  C   X1
  D   X0
+2U Y1
+1.5V Y0
  B   Z1
 -2U Z0
      Cont

+5Ui -5Ui W X Y Z U

C2-F
+5Ui
C3-F
C4-F
-5Ui
C5-F
C1-F
+5Ui
C6-F
LA-F
-5Ui
RA-F

TL 084 PIN 4 +5Vi
       PIN 11 -5Vi

TL 064 PIN 4 +5Vi
       PIN 11 -5Vi

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE EKG AMPLIFIER MK1-2A
PART C

| SIZE B | CODE | NUMBER 1100201 A4 | REV a |
| DATE 3.FEB.1987 | | SHEET | |

s1

s2

+5Vi   -5Vi

C19   D15   T9   C20
0.1uF   0.1uF

+2Vi
IC5
TL064

+5Vi   R112   +1.5Vi
       33k

P11   R114   C63
                                                         15k   0.1uF
(F)
(LL)   R9   R18   10   8
        15k   30k   9 + IC5
                                         TL064
                                                         C69
        C9   C18   0.1uF
        390p 120p   R37
                                         39k
                                         R38
                                         89k
                                                      + C68
                                                        1uF
        R36   R27   R230   -2Vi   R231   C67   D3
        39k   3.9k 47E   14   2.2k   33uF   LM385
                                     IC5   Z2.5U
                                     TL064   R132   R114   C63
                                                     15k   15k   0.1uF
                                         12   R141   R140   R113
                                     13   2.7k   1.3k   33k   -1.5Vi
                                                                          R115   C64
                                                      -5Vi   15k   0.1uF

                    R149
        C74   150k
        1.5nF
+5Vi BAV99 D18 -5Vi R150
                        3.3M
P14   7   6   R148
                            + 5 30k
(RF)   R10   R151   IC5
(RL)   15k   1.1k   TL064
                                    ra1   la1
        C75
        3.9nF

                                   R47 R146 C73   R147 C72
                                   1.1k 33k 220pF   33k   220pF
Üa1   D46
4.3V   R144   8   10
BZB800   100E   + 9
             D45   IC13
             4.3V   TL084   C70   C71   R145
                    0.1uF   R233   0.1uF   100E
                                   30k

+1.5Vi
C63 0.1uF
C64 0.1uF
-1.5Vi
R114 15k
R115 15k
R112 33k
R113 33k
+5Vi
-5Vi
R140 1.3k
D3 LM385 V2.5V
-2.5Vi
C67 33uF
R141 2.7k
R132 15k
R231 2k
C68 1uF
IC5 TL064
C69 0.1uF
R37 39k
R38 39k
IC5 TL064
+2Vi
-2Vi
la1
C72 220pF
C73 220pF
R147 33k
R146 33k
ra1
C71 0.1uF
R145 100E
R47 1.1k
R233 30k
s2
R230 50E
R27 3.9k
R36 39k
IC5 TL064
C20 0.1uF
-5Vi
BC847 T9
MMBD914 D15
R18 30k
C18 120p
C9 390p
+5Vi
C19 0.1uF
R9 15k
R148 30k
R149 150k
R150 3.3M
C74 1.5nF
IC5 TL064
-5Vi
BAV99 D19
R151 1.1k
C75 3.9nF
+5Vi
R10 15k
IC13 TL084
R144 100E
C70 0.1uF
D45 4.3V
D45 4.3V
P11 (F) (LL)
P14 (RF) (RL)
s1

TEST

BUS

LED1

R217
1.1k

+5Ui
+5Ui

R216
150k

R215
30k

IC8
TL064
4
7
11

+5Ui
-5Ui
-9Ui

R214
3.3M

C124
3.8nF

1N914
D16

R213
1.1k

C121
100nF

IC8
TL064
9
8
10

C123
390pF

R212
30k

T12
BC847

R220
5.1k

-9Ui

R219
47k

D2
1.25V
MP5010

R218
47k

-9Ui

C127
1uF

-9Ui

BAV99
D22

C120
100nF

R221
30k

-9Ui

R222
150k

IC8
TL064
14
12
13

R224
150k

R225
1.5M

-9Ui

R223
150k

C122
3.9nF

ST 7

IC20/TL062
Pin 4 -12V
Pin 8 +12V

ST 7

NICHT BESTUECKT

ST7

AIN 7

AIN 2

AIN 1

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE EXG AMPLIFIER MK1-2B
EXT.DC INPUTS

SIZE B | CODE | NUMBER 110201 A8 | REV a

DATE 1.MAI 1997 | SHEET

IC9&10/TL064
PIN 4 +12U
PIN11 -12U

DC1
BU4

DC2
BU5

DC3
BU2

ST7

ES0
a19

ES1
a20

ES2
a21

R197 47k
R198 47k
R199 47k

C113 15nF
C114 15nF
C115 15nF

10 9 IC11 TL064 8
3 2 IC11 TL064 1
12 13 IC11 14 TL064
5 6 7 IC11 TL064

+12V
+12V
+12V

D84 BAV99
D85 BAV99
D86 BAV99

R203 62E
R204 62E
R205 62E

C116 100nF
C117 100nF
C118 100nF

R207 27E
R208 27E
R209 27E

Si1 F100mA
Si2 F100mA
Si3 F100mA

-12V
-12V
-12V

CH1
CH2
CH3

BU 2

DC4
+
-

IC11/TL064
Pin 4 +12V
Pin11 -12V

SCHILLER AG, CH-6340 BAAR
ALTG6ASSE 68

TITLE EKG AMPLIFIER MK1-2A
DISPOSITION

| SIZE B | CODE NUMBER | 1100203 | REV A |

DATE 25.SEPT 1986   SHEET

PATIENT   TEST   SCOPE   DC2   DC1

BU1   BU8 LED1   BU2   BU3   BU5   BU4

SCHILLER AG, CH-6340 BAAR
Altgasse 68

TITLE ECG AMPLIFIER MK1-2 CS12
DISPOSITION

SIZE	CODE	NUMBER	REV
B		1200X03	A

DATE 5.JAN.1987 SHEET

ST7

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

| TITLE | EKG AMPLIFIER MK1-2D   CS 12 |
| | DISPOSITION |

SIZE	CODE	NUMBER	REV
B		1200203	A

DATE 28.JULI.1989   FILE:MK1\MK12DISP

SECTION 5

POWER SUPPLY CIRCUIT MK2-6

ST 14

GL1
4*SB350

P20 P21 P22 P23

TX1

P14 P15 P16 P17 P18 P19

TRANSFORMER
connectet
for 220V

R2
NTC
82E

R1
VDR
250V

P10
P11

LP1

P12
P13

LP1
for
220V

P7 P8
P6 P9

S1
MAINS
SWITSCH

P1 P4
P2 P5
P3

Si1
2*T200mA

LINE
FILTER

P
N
E

190-240VAC/50HZ

B

RFP6P08
T3

S — D

L4
300uH

+UB

1N4007
D5

P24

S13
T2A

R25
30K

Z18V
D16

C23
10nF

C24
150nF

C25
150nF

+ C26
470uF

+ C27
470uF

ST 15

P25
P26

NP 12V
1,8A/h

R26
4,7K

LL4148
D15

P29

SWNN

P27
P28

LL4148
D34

ON/OFF
uP

R31
10K

8a,c

ST6

R30
75K

E   T5
          B
     BC857
C

R29
330K

C28
10uF

C   T4
            B
E   BC847

R28
330K

R27
68K

-14V

C

LL4148
D14

BATT.
OPERATION
ON/OFF

17a,c

ST 6

D

E

SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			

TITLE	POWER SUPPLY MK2-6(A) OF			
SIZE	CODE	NUMBER		REV
B		1100601 0F		A
DATE 21.MAI 1986		SHEET		

SCHILLER AG, CH-6340 BAAR			
ALTGASSE 68			
TITLE	POWER SUPPLY MK2-6(A) BC		
SIZE **B**	CODE	NUMBER 1100601 BC	REV **A**
DATE 21.MAI 1986		SHEET	

U invut 18 - 30V
Si2
F1,25A

13.8V/2.3 C
1N5400

FERRIT
PERLE

L1 300uH
C1 2200uF
C2 150nF
C3 150nF
C4 100uF
C5 150nF

SB150 D2
SB150 D3
1.5UD6 R18 27E
C7 10nF
L2 1.5UD6
L3 520uH
R19 0.12E
C8 150nF
C9 470uF
C10 470uF
D4 1N5400
R24 3K

BAU99 D1a
BAU99 D1b
R3 5,1K
R4 100K
C21 150nF
C22 10nF
79L15 U1

LL4148 D36
R38 27E
R17 220E
R16 27E
C19 150nF
C18 10uF
TSC427 U11

R14 180K
C13 330pF
C12 120pF
R7 75K
C14 2,2nF
R15 2K

3524AH U9
OUT OUT COMP +5Vref
C15 10uF
C16 150nF
C17 680pF
R6 2K
R5 33K

R13 1.5M
LL4148 D6
C11 150nF
062 U4
R12 7,5K
R11 1,5K
R10 2,2K
R8 4,7K
R9 500E

R20 11K
R21 5,1K
LL4148 D7
LM336 2S.8V D8
R22 10K
R23 1K
062 U4

TIC116 T2

T1 26P03

ST 6

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE	POWER SUPPLY MK2-6(A) 12V +/-12V		REV
			A
SIZE	CODE	NUMBER 1100601 12V	
B			
DATE 21.MAI 1986			SHEET

+UB

L10
300uH

C70
150nF

C71
150nF

R88
5,1K

R91
20K

C77
680pF

C78
150nF

R92
2K

+5Vref
U12
OUT 11
OUT 12
COMP
8524AN

C74
10uF

U11
OUT
OUT
TSC427

C72
470uF

R90
27E

R89
27E

C79
150nF
T19
RFP6P08
S
G
D

C73
330pF

C75
330pF

R95
330K

C76
120pF

R93
330K

C80
10nF

R96
2K

L11
800uH

D32
SB150

R97
0,27E

R94
2K

C81
150nF

C82
470uF

C83
470uF

C84
150nF

D33
1N5339B
25,6V

C79
10uF

ST 6

+5V

23,24,
25,26,
27a,0

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE POWER SUPPLY MK2-6(A) 5V
5V

SIZE B
CODE
NUMBER 11065G1 5V
REV A

DATE

MOTOR CONTROL

STEPPER
MOTOR

ST 13

L293

U7

L297

U6

ST 6

MOTOR CONTROL

CLOCK

MOTOR ON/OFF

MOTOR ON/OFF

MOTOR CLOCK

uP ON/OFF

BATT LOW

BATT OPERA- TION

-12V

+12V

+5V

ST 6

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE	POWER SUPPLY MK2-6 PIN PINOUT ST 6		
SIZE B	CODE	NUMBER 1100601 PIN	REV A

ST 6

ST 12

ST 8

ST 14

grün P20
rot P21
blau P23
braun P22

ST 13

ST 15

GND

P18 P19 P15 P14
P16 P17
P13
P
R1 VDR250V
R2 NTC
P26
P110 P8
P34
P35 GND
P29

CS2 6800µF
CS1 6800µF
CS0 6800µF

C1 2200µF 40V

8x SB150
GL1: 4x SB350

U16 L297

C34 470µF
C35 L297

L3 500µH

T1 RFP6 P08

U15 3524AU

U14

R90 27E
R68 2,2k
TSC 427
C73 10µF
P92 2k

C72 470µF

L11 800µH

T18 RFP6 P08

C55 100µF
C57 470µF

L5 100µH

T8 BU671A

C26 2x470µF
C27

L4 300µH

L10 300µH

AT-6 Power Supply and Charger Circuitry

- Main input and unregulated DC output
- Charging principle, PWM (pulse width modulation) circuit.
- Overvoltage protection of the battery charging circuit output (point B on the schematic power supply MK2-6 '13.8V Batt. charger)
- Operation detection modes, battery or main (point C on the schematic power supply MK2-6 '13.8V Batt. charger)

1.   AT-6 Mains Input Circuit

The mains supply is first connected to a line filter module including two main fuses each rated at 200 mA (S.B.). The 110 Vac version is equipped with another main line filter which is adapted for 110 Vac use (110 Vac filter P/N: 4.270002), the fuses being rated at 400 ma (S.B) each. The mains is connected to the mains transformer over a dual-pole mains switch including a monitoring lamp (190..240Vac = green pushbutton, 110Vac = red coloured switch button P/N 4.220010 + 4.220050 for the cover). Mains connection is indicated via the integrated mains switch bulb LP1 which also proves that the two main fuses are not blown. Overvoltage protection is provided by a VDR (variable differential resistor), which suppresses possible mains spikes in order to protect the mains transformer. The mains transformer can be adapted for both mains selections by means of connecting the primary windings in series for 190..240Vac and in parallel for the 110Vac mode.

The mains transformer secondary coils (parallel connected) generate an AC output varying between 20 and 25Vac between St-4 connector pins P20 and P23 (see power supply schematic 190-240Vac/50 Hz). The unregulated output voltage (point A) is connected to a full-wave bridge rectifier (4 schottky diodes, SB 350) which generates an unregulated DC output corresponding to around 25 Vdc ($\pm$ 20 %). The DC current consumption over the secondary ´fuse Si2 (1.25 Adc) may change between 100 mA and 700 mA, depending on the charging state of the battery. The standby DC current surge over Si2 will generally be around 170 mA ($\pm$ 20 %) **If no battery is connected** to the power supply and the AT-6 stays in standby mode (no printing process). A 70 % discharged battery will cause a current increase across Si2 up to **1.1 Adc**. Once the battery has reached the final charging phase (around 90 % of charge), the current will decrease to the nominal standby current of $\approx$**170 mA**. See point 5 for more details about calibration of the battery charge circuit.

2.   AT-6 Battery Charger Circuit Description

The detection of the presence of the mains supply is provided by sensing the charging voltage which corresponds to $\approx$14.5 Vdc (at 20°C) at the D4 anode side when the mains supply is ON, thus 0V when the mains is switched OFF (the battery voltage can be measured at the cathode of D4). The charging voltage is controlled by a PWM circuit (U9, 3524). The PWM circuit pumps energy (current) over the series inductance L1 (300 µH) by switching the FET (T1) **ON**, thus providing the characteristic function d_l / d_T. When the FET is off, the function d_U / d_T occurs (voltage build-up). The purpose of the PWM circuit is to keep a constant regulated voltage (without being affected by temperature or load changes) by adapting the duty-cycle ratio of the ON/OFF phase which drives the power MOSFET Tl.

The duty-cycle ratio, which influences the output voltage, is controlled by the PWM circuit by means of sensing the output regulator voltage output (point B on power supply circuit, right after rectifier diode D4). The PWM differential error amplifier compares the inverting input of the voltage input sense (Pin #1) with the internal 5V reference of the 3524. If for any reason the charging output voltage increases to 15.8 V, the output of the voltage divider network (R12, R10/R11, R8, R9) connected after the non-inverting voltage follower (U4) corresponds therefore to 5Vdc, thus switching the PWM output OFF (differential input = 0). Current limiting protection is performed over the current sense resistor R19 (0.12Ω) connected to the current sense amplifier input of the 3524 regulator.

The current limit threshold at the input of the 3524 current sense comparator monitors the voltage drop across the 0.12Ω sense resistor, the activation threshold is circuit defined to be active (regulator shut-off) by the condition U.sense = ≥ than 200mV. Thus when the power supply provides a maximum available current of 1.6 A, voltage drop of 200 mV across R19 (0.12Ω) would therefore correspond to I= U/R = 1.667 Adc.

NOTE: The lead-acid battery is automatically charged, even if the AT-6 has been switched off (keyboard ON/OFF fnc). Unless the main switch (green front switch) has been switched off, the charging circuit is inoperate.

3.   Charging Circuit Overvoltage Protection

In order to protect the battery from an excessive charging voltage (lead-acid batteries are very sensitive to overvoltage), the circuit also consists of a power input crowbar which short-circuits the DC input (18..30 Vdc) thus tripping Si2 (1.25 A). The circuit works by means of sensing the output charging voltage at the output of diode D4 (cathode, see schematic point B). OpAmp U4b is connected as a voltage follower (impedance converter) and feeds the "sensed" voltage back to the input of OpAmp U4a (comparator) via voltage divider network (R20 & R21). The comparator reference corresponds to 5 Vdc and is generated by the LM 336 bandgap reference circuit Z5.0V. As soon as the charging voltage exceeds ≥15.8 Vdc, the potential at the comparator non-inverting input (pin 3) will correspond to 5Vdc thus causing the comparator output to saturate the gate of crowbar SCR T2 (thyristor TIC 116, point B on the schematic power supply MK2-6 '13.8V Batt charger). As a result of firing the SCR, the DC unregulated output will instantly short to ground thus blowing Si2 fuse.

4.   Temperature Compensation

The charging circuit is also temperature compensated by means of an NTC thermistor resistance (R11) connected to the voltage feedback path, if the ambient t° increases, the NTC resistance decreases thus affecting the divider network and reducing the output voltage charge.

NOTE: The NTC (negative temperature coefficient) resistance value is given by 1.5 kΩ at room temperature (20°C).

5.   Battery Charge Calibration

Lead-acid batteries are high quality, maintenance-free accumulators and have a long operational life in standby or cyclic applications. Lead-acid batteries are charged by a constant VOLTAGE, unlike NiCd cells which are charged by a constant current regardless of the voltage. The manufacturer of these batteries specifies that the EMF charge to the element is defined as 13.6 Vdc at 23°C (see the table 'U = f(t°)'. The calibration of the correct charging voltage requires great care and should not be considered as a 5 minute job (see service manual procedure), otherwise the life-time of the accumulator will be greatly reduced. The fundamental conditions for a successful calibration are:

1. Record the ambient temperature with a digital temperature instrument by placing the sensor in the case of the AT-6 (in the vicinity of the NTC thermistor). The reading should be stable and within 0.5° of max. tolerance.

    CAUTION: make sure that the temperature probe does not touch any components or heat sink of power devices, otherwise the probe or the circuit may be destroyed.

2. The calibration of the specific charge voltage (according to the tables) has to be done with the battery connected to the machine, the battery acts as a current regulator (variable load) !

3. You **must** be sure that the calibration is carried out with a **fully charged** battery, otherwise the charging voltage will be false by the lower chemical inner resistance of the lead-acid element!

4. Once calibrated, the charging voltage has to be monitored for a period of at least 12 hours (always in the fully charged state).

NOTE: The lead-acid battery is a long-life, maintenance-free accumulator which has a nominal voltage of 12 Vdc and a current capacity of 2 Ah (2 ampere/hour).

6.   Battery/Mains Operation Mode Detection (schematics 13.8V Batt. charger & power supply)

The battery/mains detection is purely based on 1 diode and 1 data selector/MUX IC on the µPcb. The Anode of diode D4 is "LOW" once the AT-6 works on the battery (no mains). When the mains is ON, the battery is charged over point "B" by a voltage corresponding to ≈13.8 Vdc, the **Anode of D4** is now connected to around 14.8 ..15 Vdc. The path of the MAINS "ON" detection started at point "C" where ≈14.8 Vdc is connected to D14 cathode (LL4148), this point is called "BATT OPERATION ON/OFF". The Anode of D14 is directly connected to the µProcessor Pcb over the backplane main connector ST6 17a, c to µPcb Europe type connector **ST-2 pin 28c**. The signal "BAT" provided on the µPcb by D14, is then connected to pin # 10 of a quad 2 input data selector/MUX (three state outputs). Pin # 10 of the HC257 MUX is connected to a 10kΩ pull-up resistor connected to Vdd (+5Vdc), therefore when the mains in **ON**, D4 Cathode has about 14.8..15 Vdc thus will not conduct and the Data line input # 10 (on the schematic defined as **Input 3B**) will be tied up to +5Vdc over the Pull-up resistor. On the other hand if the mains is OFF, the diode will conduct to GND and pin # 10 of the HC257 MUX will change to LOW (≈1.5Vdc). The change of status of the MUX input # 10 is then interpreted as a 4 Bit nibble (D8..D11) transferred to the data bus therefore indicating the status of the battery mode.

NOTE: With a standard measuring tool like an oscilloscope, you may not clearly identify the nibble status change on the Data bus when toggling between the modes. A logic analyzer would be a better adapted tool for that kind of digital analysis. This is why it would be preferable to limit the check to the input of the MUX gate (pin #10).

SECTION 6

BACKPLANE PCBs
## INTERCONNECTION DIAGRAM
MK2-4

	Drawing No.
Backplane	1100401 C1
Backplane Signals Despatch	1100401 C2
PCB Layout	1100403

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE BACKPLANE MK2-4

| SIZE B | CODE | NUMBER 1100401 C1 | REV A |
| DATE 22.MAI | 1986 | SHEET 1 | |

TITLE	BACKPLANE	MK2-4 DB

SIZE	CODE	NUMBER		REV
B			1100401 C2	A

DATE	22.MAI	1986	SHEET

ST 1

ST 2

ST 7

ST 6

R7

R9

R8

C2

ST 9

U1

C1

TR1

R4

R2

R3

R1

ST11

R6

R5

ST16

SECTION 7

RS-232 / VIDEO / SPIRO

SCHILLER AG, CH-6340 BAAR
ALTGASSE 63

TITLE EXTENSION CARD MK2-92
SPIRO (STAND ALONE)

SIZE	CODE	NUMBER		REV
1/1		1109201D1		A

DATE 23. NOVEMBER 88 File:MK2\MK292

SCHILLER AG CH-6340 BAAR
ALTGASSE 68
TITLE EXTENSION CARD MK2-91
VIDEO GRAPH INTERFASE
SIZE NUMBER 1109101D1 REV
2/1   A
DATE 04.OKT.88 File MK2\MK29U

BESTUECKUNG MK 2-92 (BESTUECKUNGSSEITE)

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE			
DISPOSITION MK2 - 92			
SIZE	CODE	NUMBER	REV
		1109203D1	A
DATE 23. NOVEMBER 88		SHEET	

ST3

U19 U20

U18

C18 C25

C15
U6
C14
U7
C13 C27
U8
C12
U9
C6 C5
C3 C2

U3
C24
U10 C10
U5 C22
U1
U11 C11
U4 C23

C20

U15 C16
C9

U2 C21

U17 C26
C4 C1

R1 C7
U12 C19
R2 C8
U16 C17
R3
U14

ST1

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE

DISPOSITION MK2 - 91

SIZE | CODE | NUMBER
1109103D1

REV
A

DATE 23. NOVEMBER 88 | SHEET

SECTION 8

SERVICE INFORMATION

CARDIOVIT AT-6

## Service Information

1. EQUIPMENT NEEDED

Oscilloscope
Analog Meter
3 pieces of wire (approx. 6")
1 short (low capacitance) tweaker
1 low capacitance screwdriver
soldering iron
1 small Phillips screwdriver
1 small standard screwdriver

2. OPENING UP THE UNIT

1. Pull out and remove the white contrast control knob from the right-hand side of the unit.

2. Turn the unit over and remove the four Phillips screws in each corner of the unit. You will also need to remove the two standard screws located in the centre, along the side, if they are present.

3. Using both hands, hold the top and bottom cases together and turn the unit upright. BE CAREFUL !

4. Gently lift up on the front side of the top cover removing the cable connections as they appear. Refer to Figure 1 for connector locations. This will expose the inside of the unit.

AT-6 BLOCK

3.   MICROPROCESSOR

With the exception of battery replacement and clock adjustment, the microprocessor must only be serviced by the manufacturer. The entire board is therefore replaced in the field.

3.1   Board Replacement

Board replacement is fairly straight forward. Remove the two Phillips screws that hold the microprocessor down. Refer to Figure 1 for location. Pick up on the outer edge of the board and gently pull it away from the interconnect board.

3.2   Battery Replacement

The battery backup for the real time clock circuit is powered by a 3.5V Lithium battery. If the battery voltage goes below 2.0V, battery replacement is required. To replace the battery, first remove the microprocessor board. Turn the board over, desolder the old battery and insert the new battery. Readjust clock frequency for the new battery.

3.3   Adjusting Clock Frequency

The clock frequency is adjusted by variable capacitor CT1. Refer to Figure 1 for location. With your oscilloscope attached to pin 15 of U3 (see Figure 1 for location) adjust CT1 with a low capacitance tweaker for a 4ms duty cycle.

NOTE: If there is no square wave at pin 15 of U3, enter the day of the week one time via the keyboard.

3.   μCOMPUTER BOARD

Mit Ausnahme vom Ersetzen der Batterie und dem Richten der Uhr wird dieses Board ausschliesslich vom Hersteller bearbeitet. In den Servicestellen wird deshalb bei anderen Defekten gleich das ganze Board ersetzt.

3.1   Board ersetzen

Das Erstzen des Boards ist einfach. Nachdem das neue Board eingesetzt ist, muss überprüft werden ob alle Muttern fest angezogen sind und ob die Verbindungskabel ST4 und ST5 richtig eingesteckt sind. Nullinien-Offset und Verstärkung der drei Schreibmodule MK1-7 müssen neu eingestellt werden.

3.2   Batterie ersetzen

Der Echtzeituhr-Schaltkreis ist von einer Lithium-Batterie gespiesen, die einen ununterbrochene Betrieb von bis zu 10 Jahren gewährleistet. Sobald die Spannung über der Batterie auf unter 2,0V fällt, muss sie ersetzt werden. Nachdem der Oberteil des Gehäuses entfernt worden ist, kann die alte Batterie ausgelötet werden. Die neue Batterie wird eingelötet und die Uhrenzeitbasis neu eingestellt.

3.3   Abgleich der Uhrenzeitbasis

Die Uhrenzeitbasis kann mit dem Trimmer neben dem IC M3000 oder M3002 mit Hilfe eines isolierten, kapazitätarmen Abgleichwerkzeuges eingestellt werden. Ein Rechteck-Signal von 256,0Hz ist am Pin 15 vom M3002 vorhanden. Falls dies nicht der Fall ist, muss der Wochentag einmal über die Tastatur eingegeben werden. Der Trimmer muss so eingestellt werden, dass eine sehr genaue Angabe auf dem Frequenzzähler erscheint.

GND

trimmer

256.0 Hz
(pin 15)

M3002

VARTA
ER 1/2 AA

4.   ECG AMPLIFIER BOARD

1.   In the test mode, some diagnostic parameters of ECG amplifier appear on the LCD. The following values should be shown on the LCD in the first column:

Uref+ (positive reference voltage)		1950 . . . 2050mV
Uref- (negative reference voltage)		1950 . . . 2050mV
Udif (Uref+ minus Uref-) target: 4000		3960 . . . 4040mV
Uoff (Uref+ plus Uref-) /2		-50 . . . +50mV
Calib. (Udif) / 4	target: 1000	990 . . . 1010mV
U+ (3.2*x)	target: 5Vi	1300 . . . 1900mV
U- (3.2*x)	target: -5Vi	-1300 . . . -1900mV

NOTE: Slight deviations of the Udif may be adjusted in the field, but any other deviations require replacement of the board and repair by the manufacturer.

2.   The second column on the LCD shows the offset value of the final amplifier stages. After pressing **R** (resetting) all values should lie within -400 to +400mV.

3.   The third column (input DC-offset of the electrodes in mV) should show values between -40 and +40mV if the patient cable is shorted or an ECG simulator is connected.

4.1   Board Replacement

First remove the microprocessor board and remove the two posts that the microprocessor was screwed into. Rfer to Figure 2 for locations. Remove the Phillips screw located at the patient connector (Figure 2) and lift the board slightly. Gently pull it away from the interconnect board to remove.

4.2   Adjustment

In the test mode, adjust P1 on the ECG amplifier for a reading of 4000mV for Udif on the LCD. Refer to Figure 2 for P1 location.

4.   EKG-VERSTÄRKER

1.   Im Testmodus erscheinen einige diagnostische Parameter vom EKG-Verstärker auf dem LC-Bildschirm. Die folgenden Werte sollten angezeigt werden:

Uref+ (positive Referenzspannung)		1950 . . . 2050mV
Uref- (negative Referenzspannung)		1950 . . . 2050mV
Udif (Uref+ minus Uref-) soll: 4000		3960 . . . 4040mV
Uoff (Uref+ plus Uref-) /2		-50 . . . +50mV
Calib. (Udif) / 4	soll: 1000	990 . . . 1010mV
U+ (3.2 * x)	soll: 5Vi	1300 . . . 1900mV
U- (3.2 * x)	soll: -5Vi	-1300 . . . -1900mV

HINWEIS: Leichte Abweichungen von Udif vom Nominalwert können in der Servicestelle abgeglichen werden. Alle anderen Abweichungen von den Nominalwerten weisen auf Schaltdefekte hin und verlangen eine Ersetzung des fehlerhaften Boards, welches nur vom Hersteller repariert werden kann

2.   Die zweite Kolonne zeigt die Offset-Werte der Leistungsverstärkungsstufen. Wenn die Taste **R** gedrückt wird, sollten die Werte zwischen -400 und +400mV liegen.

3.   Die dritte Kolonne (Eingangsoffset-DC-Spannung der Elektroden in mV) sollte Werte zwischen -40 und +40mV aufweisen, wenn das Patientenkabel kurzgeschlossen oder mit einem Simulator verbunden ist.

4.1 Board ersetzen

Zuerst wird das µComputer-Board MK-1 entfernt. Dann müssen die vier Schreiben (1) und die zwei Distanzbolzen (2) entfernt werden. Nachdem die Kabel ST10 und ST19 ausgezogen sind, wird die Backplane MK1-4 zusammen mit dem EKG-Verstärker MK1-2 herausgenommen. Ein neues Board MK1-2 wird in die MK1-4 eingesteckt und alle Teile wieder eingebaut. Das Gerät wird in den Test-Modus geschalten (Taste **T** drücken). Die auf dem Bildschirm erschienenden Werte müssen nun geprüft werden. Die Erstzboards sind vorabgeglichen und benötigen keinen zusätzlichen Abgleich.

4.2 Abgleich

Zwischen den Testpunkten TP3 und TP4 wird der Spannungsunterschied gemessen. Mit Trimmer P2 wird die Spannung auf einen Wert von 4.0Vdc eingestellt. Im Test-Modus wird der Trimmer P1 der Wert von Udif auf dem Bildschirm 4000mV eingestellt.

GNDi

TP1 TP2 TP3 TP4 TP5
−5Vi   +2Vref
    +5VI   −2Vref

Stück Nr.		Liegenstand Sachharbon	Pos. Req.	Material Verbare		Model Modes	Bemerkungen Observatore
#	I	Änderungen: Modificatione:				Ersetzt durch Remplace par Ersetz für Remplace	
		EKG-Verstärker MK1-2A SERVICE INFORMATION			Maßstab Echele	Gezeichnet Dessine Geprüft Contrôle Gesehen Vu	
		SCHILLER AG, CH-6340 BAAR			1100205 c		

8-7

5. ADJUSTMENT OF BATTERY CHARGER

The charging voltage of the battery is temperature dependent. Its vale is adjusted by means of R9 according to table 1. The charging voltage must be measured directly at the battery contacts.

IMPORTANT: Adjustment of the charging voltage must be done at low charging current (battery fully charged) !

5. EINSTELLUNG DER AKKUMULATOR LADESPANNUNG

Die Akkumulator Ladespannung ist abhängig von der Umgebungs-Temperatur. Sie wird mit R9 gemäss Tabelle 1 eingestellt. Gemessen wird die Ladespannung direkt am Akkumulator. Bei einer Kontrollmessung muss der gemessene Wert innerhalb des min. und max. Wertes der Tabelle sein.

WICHTIG: Die Einstellung der Ladespannung muss bei kleinem Ladestrom erfolgen (Akkumulator voll geladen), da durch die Erwärmung des Schalterreglers bei grossem Ladestrom (100mA) die Ladespannung etwas absinkt (ca. 0,8V).

TABLE / TABELLE 1 CHARGING VOLTAGE BETWEEN -10 AND +50°C LADESPANNUNG ZWISCHEN -10 UND +50°C			
Temp (°C)	min (V)	typ (V)	max (V)
-10	14.3	14.5	14.6
-5	14.1	14.3	14.5
0	14.0	14.2	14.3
5	13.9	14.1	14.2
10	13.7	13.9	14.1
15	13.6	13.8	13.9
16	13.6	13.8	13.9
17	13.55	13.75	13.9
18	13.55	13.75	13.85
19	13.55	13.7	13.85
20	13.5	13.7	13.8
21	13.5	13,65	13.8
22	13.45	13.65	13.75
23	13.45	13.6	13.75
24	13.45	13.6	13.7
25	13.4	13.55	13.7
26	13.4	13.55	13.65
27	13.35	13.5	13.65
28	13.35	13.5	13.6
29	13.35	13.45	13.6
30	13.3	13.45	13.55
31	13.3	13.4	13.55
32	13.25	13.4	13.55
33	13.25	13.4	13.5
34	13.25	13.35	13.5
35	13.25	13.35	13.45
40	13.15	13.25	13.4
45	13.1	13.2	13.3
50	13.05	13.1	13.25

6. ADJUSTMENT OF MOTOR DRIVE CURRENT

1. The current consumption of the stepper motor is measured across R55 (0.1 Ohm), corresponding to test points T1 and T2.

2. Set for manual mode 25mm/s and start motor.

3. Adjust R48 for a motor current of 90mA (equals 9mV voltage drop across R55).

IMPORTANT: Voltage probe must be isolated from ground potential!

6. EINSTELLEN DES MOTORSTROMES

1. Die Stromaufnahme des Schrittmotores kann Spannungsmässig über einem eingebauten Messwiederstand (R55/0,1 Ohm) gemessen werden. Messpunkte T1 und T2.

2. Im Manuellen Betrieb Papiervorschub auf 25mm/s einstellen und Motor starten.

3. Mit R48 Motorstrom auf 90mA (entspricht 8mV über dem Messwiederstand R55) einstellen.

WICHTIG: Spannungs-Messung über dem Messwiederstand R55 erdungsfrei!

SCHILLER AG, CH-6340 BAAR
ALTGASSE 68

TITLE	POWER SUPPLY HK2-6 SERVICE INFORMATION		
SIZE	CODE	NUMBER	REV
B		1180685 d	A

7.   PAPER MARK DETECTOR

The paper mark detector is used to sense the black mark which is on the paper. It tells the unit where to start printing and when to stop. If the unit is giving an error message of "CHECK PAPER" or "REFILL PAPER" the adjustment procedure should be carried out.

7.1   Adjustment

1. With your soldering iron and the two pieces of wire, attach one wire to point 'A' and the other to point 'B' on the interconnect board as shown on Figure 7.

    NOTE: It is easier to solder your wires on the circuit side of the board.

2. Connect your oscilloscope or meter to the end of each wire ('A' = '+' and 'B' = '-'). Run the wires to the outside of the unit and put the cover on, attaching all cables but the LCD again for ease of adjusting.

3. Turn the unit on. Press **3** (100mm/s) and **4** (+10). This puts the unit into 10mm/s speed. Press **M** to put the unit into manual recording mode. With your tweaker in one hand, pick up the top cover and reach inside the unit. Insert the tweaker into TR1 (refer to Figure 1).

4. Press the **START** key. Observe the scope or meter and adjust TR1 such that the following voltage levels are measured:

No paper mark:	0.4 - 0.6V
Paper mark:	3.5 - 4.0V

    NOTE: If there is a problem in getting the voltage to adjust down to 0.5V, you will need to check the physical placement of the paper sensor. The mount may be loose or the mount may have been bent in some way. If the mount is not loose, then bend the sensor mount slightly upwards. If you watch your scope or meter while doing this, and observe the voltage level, you can tell when it is in the right position.

When the adjustment is correct and paper runs with no error message, press the **STOP** key and turn the unit off. Remove the top case and the wires that were soldered to points 'A' and 'B'. Reassemble the unit and give a final check.

7.   EINSTELLEN DES PAPIERMARKENDETEKTORS

Am R2 und GND Voltmeter oder Oscilloscope anschliessen. Papiervorschub auf 10mm/s und manueller Betrieb einstellen. Motor starten. Eingestellt wird TR1 so dass folgende Spannungspegel gemessen werden können:

keine Marke:	0,4 - 0,6V
Marke:	3,5 - 4,0V

8.   PRINTER TIMER

The printer timer which is located on the underside of the top cover is responsible for setting up the timing to the printhead. This is dependent upon the paper speed and the millivolts per division.

This adjustment needs to be done if the printhead adjustment did not help the light printing or if there are dashes in the ECG.

8.1   Board Replacement

Remove the top cover and lay it so you are looking at the underside. Remove the two screws holding down the Printer Timer Board. Refer to Figure 3 for locations. Disconnect ST10 from the printhead and remove the board. Replace and secure it back down with the two screws.

8.2   Adjustment

1. Locate the Printer Timer Board (see Figure 3) and solder wire to R4 (see Figure 5).

2. Disconnect ST10 from the thermal printhead.

3. Connect a 30kOhm resistor between pins 3a and 4b on ST10 as shown in Figure 5.

4. Insert a wire into pin 2b of ST10 and another wire into 6b, 7b or 8b for GND connection. Refer to Figure 5 for location.

5. Put top cover back on unit and connect all cables, but the cable to the LCD. Refer to Figure 1. This will allow you to raise the cover to make your adjustments.

6. Connect your ground lead to the wire connected to either pin 6b, 7b or 8b and the positive to the wire connected to R4.
    CAUTION: Ensure that the wire going to pin 2b is not shorting to anything

7. Turn V2 fully counterclockwise. See Figure 5 for location. Turn the unit on (the LCD will not come on - it is disconnected).

8. Press key 1 (25mm/s) and key 4 (+10) to put the unit into 2.5mm/s. Then press key M to put the unit into Manual mode.

9. Press the START key and set charge time for C4 to 0.62ms by adjusting VR1. See Figure 6, diagram 1.

10. Press the STOP key and connect the probe to the wire in pin 2b of ST10.

11. Press the START key and adjust VR2 for the correct pulse width per Table 2 below. Refer to Figure 3 for the location of the resistance label on the printhead. Refer to Figure 6, diagram 2 for example.

When adjustment is set, turn the unit off and remove the cover. Disconnect all wires that were installed and connect ST10 back to the printhead.

Put the top cover back on, connecting all cables and ensure that the unit is operating correctly.

8. EINSTELLEN DES PRINTER-TIMER

1. Diese Einstellung ist bei ausgestecktem Thermo-kamm Anschluss vorzunehmen (ST10).

2. Am Stecker ST10 von Pin 3a zu Pin 4b ist ein Simulations-Wiederstand von 30kOhm/1% einzustecken.

3. Trimmer UR2 im Gegenuhrzeigersinn an den Anschlag drehen.

4. Oscilloscope an C4/R4 und GND anschliessen.

5. Im Manuell-Modus Papiervorschub starten (2,5mm/s).

6. Mit VR1 Ladezeit von C4 auf 0,62ms einstellen.

7. Oscilloscope an Pin 2b (ST10) anschliessen.

8. Mit VT2 negative Pulsdauer gemäss Tabelle 2 einstellen. Die Pulsdauer ist abhängig von der Thermo-Kamm Impedanz. Sie kann auf dem Thermo-Kamm abgelesen werden.

9. Papiervorschub stoppen und den Thermo-Kamm wieder anschliessen.

TABLE / TABELLE 2 PULSE WIDTHS	
Resistance marked on printhead Wiederstandswerte Ohm	Pulse width Anstiegszeit μs
200	435
205	445
210	457
215	467
220	477
225	480
230	500
235	510
240	522
245	532
250	542
255	555
260	565
265	575
270	587
275	597
280	607

9.   PRINTHEAD

The paper runs between the printhead and the paper roller on the paper tray. Therefore the pressure from one side of the printhead to the other side must be equal otherwise the paper will skew to one side. Also the printhead must be lined up with the paper roller.

There are two different adjustments which can be made for the printhead as follows:

9.1   Skew Adjustment

Remove the printhead cover by removing the two screws holding it on. Refer to Figure 4. With the paper running at 25mm/s, adjust the two screws marked Skew in Figure 4 so that the paper does not run off to one side.

9.2   Light Printing Adjustment

With the paper running at 25mm/s and a simulator attached, adjust the two screws marked Alignment for the darkest print possible.

NOTE: If printing is still not dark enough, you should carry out the printer timer adjustment.

9.   EINSTELLEN DES THERMO-KAMMES

1. abnehmen der Kammabdeckung; 2 Schrauben herausdrehen.

2. EKG-Signal einspeisen (Simulator), 10mm/s Papiervorschub und manuell Modus einstellen.

3. Mit den zwei Schrauben, die parallel zur Papierauslauffläche liegen, kann der Thermo-Kamm eingestellt werden. (auf maximale Schwärze einstellen)

4. Kammabdeckung mit 2 Schrauben montieren.

10. LCD DISPLAY - REMOVAL AND REPLACEMENT

10.1 Removing the LCD Display

1. Open up the unit as described in para. 2.

2. Remove the paper compartment cover.

2. Turn the top cover upside down.

3. Unplug the cable connecting the thermal printhead to the interface print.

4. Remove the two screws securing the thermal printhead.

5. Remove the thermal printhead (watch out for the washer and the pressure spring!).

6. Remove the four securing screws and remove the LCD display.

7. Make sure that any debris resulting from a broken or cracked screen are also removed (bits may be lying loose under the LCD display).

10.2 Installing an LCD Display

1. If necessary, insert a new screen and install the LCD display securing it with the four screws (protective washers).

2. Take the thermal printhead and place the two pressure springs in their respective indentations ensuring that the washers are located exactly over the securing holes.

3. Locate the thermal printhead ensuring that the washers are not displaced.

4. Secure the printhead with the two screws (protective washers).

5. Plug the connecting cable into the interface print.

6. Plug in the connecting cables at the back (LCD display, thermal printhead interface, paper mark detector) then with the top cover partially closed, attach the four remaining cables (thermal printhead, power connection, single cable for keyboard, motor connection, keyboard).

    NOTE: Make sure that the connections for the motor, thermal printhead power connection and the single cable for the keyboard are lying on top of the mains transformer.

7. Secure the unit with the four screws.

8. Insert the white contrast knob into its recess on the right-hand side of the unit.

9. Replace the paper compartment cover.

10. ANLEITUNG ZUM WECHSELN DES LC DISPLAYS

10.1 Ausbau des LCD Displays

1. Auf der rechten Seite des Gerätes weissen Drehknopf für die LCD Einstellung herausziehen.

2. 4 Schrauben am Boden des Gerätes herausdrehen.

3. Geräteoberteil langsam nach hinten aufklappen und alle Verbindungskabel ausstecken.

4. Papierfach-Deckel entfernen und Geräteoberteil auf den Kopf stellen.

5. Verbindungskabel vom Thermo-Kamm zum Interface-Print ausstecken.

6. Thermo-Kamm herausnehmen (die Unterlagsscheiben und Andruckfedern beachten!).

7. 4 Befestigungsschrauben herausdrehen und LCD herausnehmen.

8. Bei gebrochener oder gerissener Schutzscheibe auch diese herausnehmen (liegt lose in der Vertiefung unter dem LCD Display).

10.2 Einbau des LCD Displays

1. (evt.) neue Schtzscheibe einlegen und neuer LCD Display einlegen.

2. LCD mit 4 Schrauben befestigen (Sicherungsunterlagsscheiben)

3. Darauf achten, dass die zwei Andruckfedern in der entsprechenden Vertiefung stehen und die Unterlagsschieben genau auf den Befestigungs-Löchern des Thermo-Kammes liegen.

4. Thermo-Kamm einlegen (darauf achten, dass sie Unterlagsscheiben nicht verschoben werden).

5. Kamm mit 2 Schrauben befestigen (Sicherungsunterlagsscheiben).

6. Verbindungskabel zu Interface-Print einstecken

7. Zuerts die hinteren Verbindungskabel einstecken (LCD-Display, Thermo-Kamm Interface, Papiermarken Detektor), dann mit etwa halb zugeklapptem Geräteoberteil die restlichen 4 Kabel einstecken (Thermo-Kamm Pweranschluss, Einzelkabel von der Tastatur, Motoranschluss, Tastatur).

8. Darauf achten, dass die Verbindungen von Motor, Thermo-Kamm Poweranschluss und Einzelleitung von der Tastatur über den Netztransformer zu liegen kommen.

9. Gerät mit 4 Schrauben zusammen schrauben.

10. Weisser Drehknopf für die LCD-Displayeinstellung einstecken.

11. Papierfach-Deckel einsetzen.

11. ANNUAL PREVENTIVE MAINTENANCE AND CALIBRATION

1. Electronic calibration & checks

a. μProcessor Pcb: RTCC (real time clock circuit) 256.000 Hz check and calibration. Gold lithium battery check (Vout ≥ 2.8 Vdc, nominal 3.7 Vdc).

b. ECG amplifier Pcb: +2 Vdc & -2Vdc reference Voltage calibration. PWM ramp time (4000 factor on the TEST display). ± 5 Vdc supply of the DC/DC converter /Tolerance on both supply = 200 mV). The on board high voltage discharge protection bulb must be checked (no electrode contact !). Output fuses of the scope & load line (Ohmic test). Test of each High pass capacitor by applying + 100 mV dc offset to the input of the filter and pressing the reset key function (the offset line should be kept straight without moving away). Functional test of the ECG Pcb with a real patient. Cable test function must be checked with a good and a bad cable.

c. Power supply: every single supply must be measured by a D.V.M. (under load), no adjustment only check.

d. Printer timer \ Paper mark detection and stepper motor ad/check must be done. The printer timer 2nd monoflop must be measured according to the printer head impedance and re-calibrated if needed (Tolerance ± 10 μs).

e. Battery charge voltage calibration & check

f. The battery capacity shall be tested in continuous Rhythm mode. The AT-6 shall work for at least 1 1/2 hrs (battery must be previously fully charged). If not, the 12 V battery shall be exchanged.

g. The battery protection fuse (2A, s.b) needs to be checked

h. Check on power supply MK2-6 (Batt. charge circuit) for square wave signal Vss 30V at 54 kHz (between 47 and 60 kHz)

j. The display contrast adjustment needs to be checked (from max..min).

2. Mechanical adj, replacement / Test:

a. paper table: The paper table rubber cylinder Schiller P/N 4.410046 (including the cylinder bearing, P/N 4.410041) may be exchanged after 1 Year of use (optional). The cylinder Nylon gear must be optically checked and if needed exchanged. After exchanging the rubber cylinder and readjusting the printer timer monoflop, the unit must show good printing results. If not, recheck with the lowest speed in manual mode at 12 CH and activate the 1 mV function continuously.

b. Printer head readjustment (optional) only with weight gauge.

c. Photocell replacement and readjustment (P/N 3.900703)

d. Keyboard test (each key shall be depressed and correctly decoded)

3. Accessories

The patient cable shall be thoroughly measured and tested incl. all peripheral connectors.

4. Cleaning procedures:

The electronic board compartment needs to be free of dust (air pressure low to clean) and kept free of any acids or aggressive solutions (optical checks). For cleaning the machine and Pcb we advise to use any solution like Alcohol mixed with Freon (50/50), Incidin, Amocid, etc.
ATTENTION: the LCD screen shall be only cleaned with a soap/water mix.

AT-6 BOTTOM CASE OVERVIEW
W/MICROPROCESSOR

INTERCONNECT BOARD

CABLE TO PRINTHEAD

CABLE TO PAPER SENSOR

POWER TO PRINTHEAD →

WIRE TO KEYBOARD

CABLE TO STEPPER MOTOR

TR1

UAx.xa   UBx.xa   UCx.xa

LAx.xa   LBx.xa   LCx.xa

RIBBON TO LCD

SCREW

CT1

LITHIUM BATTERY

U3 M3002

RIBBON TO KEYBOARD

SCREW

FIGURE 1

AT-6 BOTTOM CASE OVERVIEW
W/ECG AMPLIFIER

FIGURE 2

AT-6 TOP COVER

KEYBOARD

PRINTER TIMER

PAPER
TRAY

PRINTHEAD

RESISTANCE LABEL

ST10

LCD

FIGURE 3

PRINTHEAD COVER

SKEW

ALIGNMENT

FIGURE 4

PRINTER TIMER

FIGURE 5

DIAGRAM 1

0,62~s

DIAGRAM 2

0,5~s → 230Ω

FIGURE 6

FIGURE 7

SECTION 9

SPARE PARTS LIST

SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba /0356/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100149		ST		MK2-1D uP-Print AT-6	1								1.0000
	001				01	Stückliste Index -		0							
	002				01	Stand 03.12.88		0							
	003				01	--------------------		0							
	050	4.490136	1.000	ST	01	uP-Print MK2-1D	0	0	1	0	00	00	00	00	1.0000
	051				01										
	096				01	Halbleiter		0								
	097				01	--------------------		0								
	100	4.650028	1.000	ST	01	uP 68HC000P10	0	0	1	0	00	00	00	00	1.0000
	101				01	U1		0								
	105	4.655007	1.000	ST	01	6732Q01	0	0	1	0	00	00	00	00	1.0000
	106				01	U16		0								
	110	4.655011	1.000	ST	01	93C46 SMD	0	0	1	0	00	00	00	00	1.0000
	111				01	U23,U55		0								
	120	4.655002	1.000	ST	01	MSM 82C53 - 5GS	0	0	1	0	00	00	00	00	1.0000
	121				01	U2		0								
	125	4.655001	1.000	ST	01	MSM 6240 GSK	0	0	1	0	00	00	00	00	1.0000
	126				01	U17		0								
	130	4.650032	1.000	ST	01	MK 4501N-15	0	0	1	0	00	00	00	00	1.0000
	131				01	U31		0								
	135	3.100183	1.000	ST	01	MK2-11 Ausf. AT-6	1	0	1	0	00	00	00	00	1.0000
	140	4.650023	2.000	ST	01	HN 27C256G-20	0	0	1	0	00	00	00	00	2.0000
	141				01	U47,U48		0								
	145	4.655003	3.000	ST	01	HM 6264 LFP-15	0	0	1	0	00	00	00	00	3.0000
	146				01	U20,U45,U46		0								
	150	4.625003	1.000	ST	01	ADC 0809 FN	0	0	1	0	00	00	00	00	1.0000
	151				01	U59		0								
	155	4.650029	1.000	ST	01	DAC 8408 HP	0	0	1	0	00	00	00	00	1.0000
	156				01	U54		0								
	160	4.675000	1.000	ST	01	TL 7705 ACD	0	0	1	0	00	00	00	00	1.0000
	161				01	U4		0								
	165	4.650018	1.000	ST	01	M 3002 B	0	0	1	0	00	00	00	00	1.0000
	166				01	U3		0								
	170	4.625000	1.000	ST	01	TL 062 CD	0	0	1	0	00	00	00	00	1.0000
	171				01	U58		0								
	175	4.625001	2.000	ST	01	TLQ64CD	0	0	1	0	00	00	00	00	2.0000
	176				01	U56,U57		0								
	180	4.645001	1.000	ST	01	74HC02 SMD	0	0	1	0	00	00	00	00	1.0000

1 SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0356/645/25.04.89/

****

tufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	181					U30									
	185	4.645002	2.000	ST	01	74HC04 SMD	0	0	1	0	00	00	00	00	2.0000
	186				01	U14,U15			0						
	190	4.645004	4.000	ST	01	74HC32 SMD	0	0	1	0	00	00	00	00	4.0000
	191				01	U8,U9,U32,U60			0						
	195	4.645006	1.000	ST	01	74HC112 SMD	0	0	1	0	00	00	00	00	1.0000
	196				01	U29			0						
	200	4.645007	3.000	ST	01	74HC138 SMD	0	0	1	0	00	00	00	00	3.0000
	201				01	U5,U6,U13			0						
	205	4.645018	1.000	ST	01	74HC139 SMD	0	0	1	0	00	00	00	00	1.0000
	206				01	U7			0						
	210	4.645008	2.000	ST	01	74HC151 SMD	0	0	1	0	00	00	00	00	2.0000
	211				01	U10,U28			0						
	215	4.645017	1.000	ST	01	74HC174 SMD	0	0	1	0	00	00	00	00	1.0000
	216				01	U11			0						
	220	4.645011	7.000	ST	01	74HC257 SMD	0	0	1	0	00	00	00	00	7.0000
	221				01	U25,U26,U27,U33,U34,U35			0						
	222				01	U40									
	225	4.645012	1.000	ST	01	74HC259 SMD	0	0	1	0	00	00	00	00	1.0000
	226				01	U22			0						
	230	4.645013	1.000	ST	01	74HC390 SMD	0	0	1	0	00	00	00	00	1.0000
	231				01	U24			0						
	235	4.645014	1.000	ST	01	74HC393 SMD	0	0	1	0	00	00	00	00	1.0000
	236				01	U12			0						
	240	4.645016	3.000	ST	01	74HC573 SMD	0	0	1	0	00	00	00	00	3.0000
	241				01	U18,U17,U21			0						
	245	4.665104	1.000	ST	01	LM 336 BM 5.0	0	0	1	0	00	00	00	00	1.0000
	246				01	D1			0						
	295				02	————————————									
	296				02	Kondensatoren			0						
	297				02	————————————									
	300	4.861100	2.000	ST	02	Chip 10 pf 0805	0	0	1	0	00	00	00	00	2.0000
	301				02	C4,C7			0						
	305	4.861330	5.000	ST	02	Chip 33 pf 0805	0	0	1	0	00	00	00	00	5.0000
	306				02	C5,C6,C18,C19,C6			0						
	310	4.861121	1.000	ST	02	Chip 120 pf 0805	0	0	1	0	00	00	00	00	1.0000
	311				02	C2			0						
	315	4.861392	3.000	ST	02	Chip 3.9 nF 0805	0	0	1	0	00	00	00	00	3.0000
	316				02	C12,C14,C16			0						

1 SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0356/645/25.04.89/

tufe

Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
320	4.861103	3.000	ST	02	Chip 10 nf 0805	0	0	1	0	00	00	00	00	3.0000
321				01	C13,C15,C17									
325	4.861333	25.000	ST	02	Chip 33 nf 0805	0	0	1	0	00	00	00	00	25.0000
326				02	C9,C10,C11,C20,C21,C22			0						
327				02	C23,C27,C28,C29,C30,C31			0						
328				02	C32,C33,C34,C35,C36,C37			0						
329				02	C38,C39,C40,C41,C42,C43			0						
330				02	C44			0						
335	4.861104	1.000	ST	02	Chip 100 nf 1206	0	0	1	0	00	00	00	00	1.0000
336				02	C1			0						
340	4.845006	1.000	ST	01	Tantal 10uF/16V	0	0	1	0	00	00	00	00	1.0000
341				02	C3			0						
345	4.845004	1.000	ST	02	Tantal 68uF/6V	0	0	1	0	00	00	00	00	1.0000
346				02	C24			0						
350	4.845002	2.000	ST	02	Tantal 33uF/15V	0	0	1	0	00	00	00	00	2.0000
351				02	C25,C26			0						
355	4.840003	1.000	ST	02	Tantal 2.2uF/16V (35V)	0	0	1	0	00	00	00	00	1.0000
356				02	C45			0						
395				03	Widerstynde			0						
396				03	-----------			0						
397				03				0						
400	4.715471	9.000	ST	03	Chip 470 Ohm 2% 1206	0	0	1	0	00	00	00	00	9.0000
401				03	R2,R20,R22,R23,R24,R25			0						
402				03	R26,R27,R29			0						
405	4.715472	2.000	ST	03	Chip 4.7 k Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
406				03	R1,R19			0						
410	4.715103	1.000	ST	03	Chip 10 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
411				03	R6			0						
415	4.715153	7.000	ST	03	Chip 15 k Ohm 2% 1206	0	0	1	0	00	00	00	00	7.0000
416				03	R7,R9,R10,R12,R13,R15,R16			0						
420	4.715303	3.000	ST	03	Chip 30 k Ohm 2% 1206	0	0	1	0	00	00	00	00	3.0000
421				03	R8,R11,R14			0						
430	4.715335	2.000	ST	03	Chip 3.3 M Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
431				03	R3,R4			0						
435	4.716153	2.000	ST	03	Melf 15 k Ohm 1% 0204	0	0	1	0	00	00	00	00	2.0000
436				03	R16,R18			0						
440	4.721007	3.000	ST	03	7x10k	0	0	1	0	00	00	00	00	3.0000
441				03	R21,R28,R30			0						
445	4.722001	2.000	ST	01	Netzwerk 5x47k	0	0	1	0	00	00	00	00	2.0000

SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0356/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	446				03	R31,R32									
	450	4.715473	2.000	ST	01	Chip 47 k Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	451				01	R33,R34			0						
	495				04	Quarze			0						
	496				04	------			0						
	497				04				0						
	500	4.680007	1.000	ST	04	Quarz NMP 24.0 MHz	0	0	1	0	00	00	00	00	1.0000
	501				04	Q3			0						
	505	4.685001	1.000	ST	04	Quarz CX-1V 32.768 A	0	0	1	0	00	00	00	00	1.0000
	506				04	Q2			0						
	510	4.680006	1.000	ST	04	Quarz NMP 20.0 MHz	0	0	1	0	00	00	00	00	1.0000
	511				04	Q1			0						
	595				05				0						
	596				05	Div. Komponenten			0						
	597				05	------			0						
	600	4.855000	1.000	ST	05	Trimmer 5-40pF	0	0	1	0	00	00	00	00	1.0000
	601				05	CT1			0						
	605	4.736001	1.000	ST	05	4.7 k PCV 215/30	0	0	1	0	00	00	00	00	1.0000
	606				05	P1			0						
	610	4.350003	1.000	ST	01	Lith. Batterie 3V CS/AT	0	0	1	0	00	00	00	00	1.0000
	611				05	B1			0						
	615	4.260064	2.000	ST	05	Messerleiste 41612 geb.	0	0	1	0	00	00	00	00	2.0000
	616				05	ST1,ST2			0						
	620	4.261023	1.000	ST	05	26-pol. Wanne gebogen	0	0	1	0	00	00	00	00	1.0000
	621				05	ST5			0						
	625	4.261022	1.000	ST	05	10-pol. Wanne gebogen	0	0	1	0	00	00	00	00	1.0000
	626				05	ST4			0						
	630	4.260036	1.000	ST	05	Stereo-Klinkenbuchse 3,5	0	0	1	0	00	00	00	00	1.0000
	631				05	ST3A			0						
	640	4.250009	1.000	ST	05	IC-Sockel 64 pol.	0	0	1	0	00	00	00	00	1.0000
	641				05	U1			0						
	645	4.250007	6.000	ST	05	IC-Sockel 28 pol.	0	0	1	0	00	00	00	00	6.0000
	646				05	U47,U48,U49,U50,U51,U52			0						
	650	4.917000	4.000	ST	05	Linsenk.schraube 2,9x6,5	0	0	1	0	00	00	00	00	4.0000
	655	4.530010	1.000	ST	05	Kabelbinder 300 mm	0	0	1	0	00	00	00	00	1.0000
	900				01				0						
	901				01	17.04.88 Umstellung von			0						
	902				01	10uF/6V auf 10uF/16V			0						
	903				01				0						

M SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0356/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	904				01	03.12.88 DF MS				0					
	905				01	R31,R32 alt 5x100k - 47k				0					
	906				01	R34 alt 100k neu 47k				0					
	907				01	-------------------------				0					
	908				01	07.12.88 Umstellung von				0					
	909				01	TM 4256 EA4-15L auf Print				0					
	910				01	MK2-11				0					
	911				01	-------------------------				0					

1 SCHILLER AG   BAUKASTEN-STUECKLISTE   Ba   /0354/645/25.04.89/
****

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100139		ST		MK1-2C EKG Verst. AT-6	1								1.0000
	001				01	Stueckliste Index --		0							
	002				01	Stand 16.11.88 999		0							
	003				01			0								
	030	4.490132	1.000	ST	01	EKG-Print MK1-2C	0	0	1	0	00	00	00	00	1.0000
	031				01	Halbleiter		0								
	046				01	------------										
	047				01			0								
	050	4.625001	11.000	ST	01	TLO64CD	0	0	1	0	00	00	00	00	11.0000
	051				01	IC1,IC2,IC3,IC4,IC5,IC6		0								
	052				01	IC7,IC8,IC9,IC10,IC11										
	055	4.625000	2.000	ST	01	TL 062 CD	0	0	1	0	00	00	00	00	2.0000
	056				01	IC12,IC20		0								
	060	4.620009	1.000	ST	01	TLO84CN	0	0	1	0	00	00	00	00	1.0000
	061				01	IC13		0								
	065	4.635000	1.000	ST	01	4013 SMD	0	0	1	0	00	00	00	00	1.0000
	066				01	IC14		0								
	070	4.635004	2.000	ST	01	4051 SMD	0	0	1	0	00	00	00	00	2.0000
	071				01	IC15,IC16		0								
	075	4.635005	2.000	ST	01	4066 SMD	0	0	1	0	00	00	00	00	2.0000
	076				01	IC17,IC18		0								
	080	4.630012	1.000	ST	01	14551	0	0	1	0	00	00	00	00	1.0000
	081				01	IC19		0								
	085	4.615002	12.000	ST	01	BC 847 B	0	0	1	0	00	00	00	00	12.0000
	086				01	T1,T2,T3,T4,T5,T6,T7,T8		0								
	087				01	T9,T10,T11,T12										
	090	4.615003	1.000	ST	01	BC857B	0	0	1	0	00	00	00	00	1.0000
	091				01	T13		0								
	095	4.615053	2.000	ST	01	IRFS 120 TRL	0	0	1	0	00	00	00	00	2.0000
	096				01	T14,T15		0								
	100	4.610059	8.000	ST	01	2N4393	0	0	1	0	00	00	00	00	8.0000
	101				01	T16,T17,T18,T19,T20,T21		0								
	102				01	T22,T23										
	105	4.610058	1.000	ST	01	J 270	0	0	1	0	00	00	00	00	1.0000
	106				01	T24		0								
	110	4.670016	2.000	ST	01	MP 501D GN	0	0	1	0	00	00	00	00	2.0000
	111				01	D1,D2		0								
	115	4.670005	2.000	ST	01	LM 385 2.5V	0	0	1	0	00	00	00	00	2.0000

Stufe	Pos.	Artikel-Nr.	Menge ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	116				D5,D16			0						
	120	4.665001	12.000 ST	01	MMBD914	0	0	1	0	00	00	00	00	12.0000
	121			01	D5,D6,D7,D8,D9,D10,D11			0						
	122			01	D12,D13,D14,D15,D16			0						
	125	4.660017	2.000 ST	01	1N5817	0	0	1	0	00	00	00	00	2.0000
	126			01	D17,D18			0						
	130	4.665002	18.000 ST	01	BAV99	0	0	1	0	00	00	00	00	18.0000
	131			01	D19,D20,D21,D22,D23,D24			0						
	132			01	D25,D26,D27,D28,D29,D30			0						
	133			01	D31,D32,D33,D34,D35,D36			0						
	135	4.600001	1.000 ST	01	4N26	0	0	1	0	00	00	00	00	1.0000
	136			01	OP3			0						
	140	4.600009	7.000 ST	01	6 N 136	0	0	1	0	00	00	00	00	7.0000
	141			01	OP4,OP5,OP6,OP7,OP8,OP1			0						
	142			01	OP2			0						
	145	4.665102	2.000 ST	01	BZX84C4V3LT1 4.3V	0	0	1	0	00	00	00	00	2.0000
	146			01	D45,D46			0						
	150	4.665000	4.000 ST	01	BAR 43 S	0	0	1	0	00	00	00	00	4.0000
	151			01	D47,D48,D49,D50			0						
	177			02	------------------			0						
	178			02	Widerstynde			0						
	179			02	------------------			0						
	180	4.715000	1.000 ST	02	Chip O Ohm	0	0	1	0	00	00	00	00	1.0000
	181			02	R236			0						
	185	4.715270	4.000 ST	02	Chip 27 Ohm 2% 1206	0	0	1	0	00	00	00	00	4.0000
	186			02	R207,R208,R209,R210			0						
	190	4.715620	6.000 ST	02	Chip 62 Ohm 2% 1206	0	0	1	0	00	00	00	00	6.0000
	191			02	R122,R123,R203,R204,R205			0						
	192			02	R206			0						
	195	4.715101	5.000 ST	02	Chip 100 Ohm 2% 1206	0	0	1	0	00	00	00	00	5.0000
	196			02	R144,R145,R152,R153,R154			0						
	200	4.715161	8.000 ST	02	Chip 160 Ohm 2% 1206	0	0	1	0	00	00	00	00	8.0000
	201			02	R80,R81,R82,R83,R84,R85			0						
	202			02	R86,R87			0						
	205	4.715561	5.000 ST	02	Chip 560 Ohm 2% 1206	0	0	1	0	00	00	00	00	5.0000
	206			02	R133,R134,R135,R136,R137			0						
	210	4.715112	24.000 ST	02	Chip 1,1 K OHM 2% 1206	0	0	1	0	00	00	00	00	24.0000
	211			02	R39,R40,R41,R42,R43,R44			0						
	212			02	R46,R47,R96,R97,R98,R99			0						

1 SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba /0354/645/25.04.89/

tufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	213				02	R100,R101,R102,R103,R118									
	214				02	R119,R120,R121,R151,R213									
	215				02	R217									
	220	4.715132	3.000	ST	02	Chip 1,3 k Ohm 2% 1206	0	0	1	0	00	00	00	00	3.0000
	221				02	R138,R140,R158									
	225	4.716202	8.000	ST	02	Melf 2,0 k Ohm 1% 0204	0	0	1	0	00	00	00	00	8.0000
	226				02	R72,R73,R74,R75,R76,R77									
	227				02	R78,R79									
	230	4.715272	1.000	ST	02	Chip 2,7 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	231				02	R141									
	235	4.717392	9.000	ST	02	Melf 3,9 k 0,1% 0204	0	0	1	0	00	00	00	00	9.0000
	236				02	R19,R20,R21,R22,R23,R24									
	237				02	R25,R26,R27									
	240	4.715512	2.000	ST	01	Chip 5,1 k Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	241				01	R125,R124									
	245	4.715752	1.000	ST	02	Chip 7,5 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	246				02	R130									
	250	4.715103	3.000	ST	01	Chip 10 k Ohm 2% 1206	0	0	1	0	00	00	00	00	3.0000
	251				01	R211,R215,R220									
	252				02	R9,R10,									
	255	4.716153	29.000	ST	02	Melf 15 k Ohm 1% 0204	0	0	1	0	00	00	00	00	29.0000
	256				02	R1,R2,R3,R4,R5,R6,R7,R8									
	257				02	R9,R10,R56,R57,R58,R59									
	258				02	R60,R61,R62,R63,R114									
	259				02	R115,R126,R127,R127,R129,									
	260				02	R131,R132,R155,R156									
	261				02	R160									
	265	4.715203	1.000	ST	02	Chip 20 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	266				02	R142									
	270	4.716303	25.000	ST	01	Melf 30 k Ohm 1% 0204	0	0	1	0	00	00	00	00	25.0000
	271				02	R11,R12,R13,R14,R15,R16									
	272				02	R17,R18,R48,R49,R50,R51									
	273				02	R53,R54,R55,R139,R147									
	274				01	R148,R189,R195,R212									
	275				02	R221,R228,R233									
	280	4.716333	3.000	ST	02	Melf 33 k Ohm 1% 0204	0	0	1	0	00	00	00	00	3.0000
	281				02	R112,R113,R146									
	285	4.717393	11.000	ST	02	Melf 39 k 0,1% 0204	0	0	1	0	00	00	00	00	11.0000
	286				02	R28,R29,R30,R31,R32,R33									

SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0354/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	287				02	R34,R35,R36,R37,R38			0						
	290	4.716473	15.000	ST	02	Melf 47 k Ohm 1% 0204	0	0	1	0	00	00	00	00	15.0000
	291				02	R88,R89,R90,R91,R92,R93			0							
	292				02	R94,R95,R116,R159,R197			0							
	293				02	R198,R199,R218,R219			0							
	295	4.716753	8.000	ST	02	Melf 75 k Ohm 1% 0204	0	0	1	0	00	00	00	00	8.0000
	296				02	R165,R172,R180,R186,R190			0							
	297				02	R193,R234,R235			0							
	300	4.716154	33.000	ST	02	Melf 150 k Ohm 1% 0204	0	0	1	0	00	00	00	00	33.0000
	301				02	R117,R149,R157,R161,R162			0							
	302				02	R163,R164,R166,R167,R168			0							
	303				02	R169,R170,R171,R173,R174			0							
	304				02	R175,R176,R177,R178,R179			0							
	305				02	R181,R182,R183,R184,R185			0							
	306				02	R187,R191,R192,R194,R196			0							
	307				02	R222,R223,R224			0							
	310	4.715155	9.000	ST	02	Chip 1,5 M Ohm 5% 1206	0	0	1	0	00	00	00	00	9.0000
	311				02	R104,R105,R106,R107,R108			0							
	312				02	R109,R110,R111,R225			0							
	315	4.715335	2.000	ST	02	Chip 3,3 M Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	316				02	R150,R214			0							
	320	4.715184	1.000	ST	02	Chip 180 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	321				02	R216			0							
	325	4.711156	8.000	ST	02	15M 1/4W 1%	0	0	1	0	00	00	00	00	8.0000
	326				02	R64,R65,R66,R67,R68,R69,			0							
	327				02	R70,R71			0							
	397				04	-------------------------			0							
	398				04	Trimmer			0							
	399				04	-------------------------			0							
	400	4.732500	1.000	ST	04	Potmeter 50 Ohm liegend	0	0	1	0	00	00	00	00	1.0000
	401				04	R230			0							
	405	4.732202	1.000	ST	04	Potmeter 2 k liegend	0	0	1	0	00	00	00	00	1.0000
	406				04	R231			0							
	410	4.732103	1.000	ST	04	Potmeter 10 k liegend	0	0	1	0	00	00	00	00	1.0000
	411				04	R232			0							
	497				05	-------------------------			0							
	498				05	Kondensatoren			0							
	499				05	-------------------------			0							
	500	4.861121	11.000	ST	05	Chip 120 pf 0805	0	0	1	0	00	00	00	00	11.0000

SCHILLER AG /0354/645/25.04.89/ Ba

BAUKASTEN - STUECKLISTE

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	501				05	C10,C11,C12,C13,C14,C15			0						
	502				05	C16,C17,C18,C79,C80			0						
	505	4.861221	2.000	ST	05	Chip 220 pf 0805	0	0	1	0	00	00	00	00	2.0000
	506				05	C72,C73		0	0						
	510	4.861391	1.000	ST	05	Chip 390 pf 0805	0	0	1	0	00	00	00	00	1.0000
	511				05	C123		0	0						
	515	4.862391	9.000	ST	05	Chip 390 pf/200V 0805	0	0	1	0	00	00	00	00	9.0000
	516				05	C1,C2,C3,C4,C5,C6,C7,C8		0	0						
	517				05	C9			0						
	520	4.861681	13.000	ST	05	Chip 680 pf 0805	0	0	1	0	00	00	00	00	13.0000
	521				05	C96,C97,C98,C99,C100,C101			0						
	522				05	C102,C103,C104,C105,C106			0						
	523				05	C107,C110			0						
	525	4.861152	2.000	ST	05	Chip 1,5 nF 0805	0	0	1	0	00	00	00	00	2.0000
	526				05	C74,C111			0						
	530	4.862152	1.000	ST	05	Chip 1,5 nF 1% 1206	0	0	1	0	00	00	00	00	1.0000
	531				05	C66			0						
	535	4.861392	14.000	ST	05	Chip 3,9 nF 0805	0	0	1	0	00	00	00	00	14.0000
	536				05	C37,C38,C39,C40,C41,C42		0	0						
	537				05	C43,C44,C61,C62,C75,C77		0	0						
	538				05	C122,C124		0	0						
	540	4.861153	14.000	ST	05	Chip 15 nf 0805	0	0	1	0	00	00	00	00	14.0000
	541				05	C53,C54,C55,C56,C57,C58		0	0						
	542				05	C59,C60,C76,C109,C112		0	0						
	543				05	C113,C114,C115		0	0						
	545	4.861104	22.000	ST	05	Chip 100 nf 1206	0	0	1	0	00	00	00	00	22.0000
	546				05	C19,C20,C63,C64,C69,C70		0	0						
	547				05	C71,C78,C81,C82,C89,C90		0	0						
	548				05	C91,C92,C93,C94,C116,C117		0	0						
	549				05	C118,C119,C120,C121		0	0						
	555	4.861154	16.000	ST	05	Chip 150 nf 0805	0	0	1	0	00	00	00	00	16.0000
	556				05	C21,C22,C23,C24,C25,C26		0	0						
	557				05	C27,C28,C45,C46,C47,C48		0	0						
	558				05	C49,C50,C51,C52		0	0						
	560	4.851224	8.000	ST	05	Chip 220 nf 1812	0	0	1	0	00	00	00	00	8.0000
	561				05	C29,C30,C31,C32,C33,C34		0	0						
	562				05	C35,C36			0						
	565	4.845000	4.000	ST	05	Tantal 1.0uF/16V	0	0	1	0	00	00	00	00	4.0000
	566				05	C65,C69,C108,C127			0						

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	570	4.845002	1.000	ST	05	Tantal 33uF/15V	0	0	1	0	00	00	00	00	1.0000
	571				05	C67			0							
	575	4.820011	9.000	ST	05	Elko 100 uF/35V stehend	0	0	1	0	00	00	00	00	9.0000
	576				05	C83,C84,C85,C86,C87,C88			0							
	577				05	C95,C125,C126			0							
	597				06	Induktivitäten			0							
	598				06				0							
	599				06				0							
	600	4.320048	1.000	ST	01	Ringkern MK1-2	1	0	1	0	00	00	00	00	1.0000
	601				06	L1			0							
	605	4.320041	3.000	ST	06	Drossel 4,7 uH	0	0	1	0	00	00	00	00	3.0000
	606				06	L2,L3,L4			0							
	697				07	Div. Komponenten			0							
	698				07				0							
	699				07				0							
	705	4.210001	4.000	ST	07	Sicherung 100 mAF 5x20	0	0	1	0	00	00	00	00	4.0000
	706				00	Si1,Si2,Si3,Si4			0							
	710	4.210051	6.000	ST	01	Sicherungsfeder 751.0056	0	0	1	0	00	00	00	00	6.0000
	711				07	zu Sicherung			0							
	712				01	Si1,Si2,Si3			0							
	715	4.260064	1.000	ST	07	Messerleiste 41612 geb.	0	0	1	0	00	00	00	00	1.0000
	716				07	St7			0							
	720	4.600006	1.000	ST	07	Prüf-Schaltbuchse grün	0	0	1	0	00	00	00	00	1.0000
	725	4.260178	1.000	ST	01	MAB 5 SH abgeschliffen	1	0	1	0	00	00	00	00	1.0000
	726				07	B3			0							
	730	4.260179	1.000	ST	01	MAB 6 H abgeschliffen	1	0	1	0	00	00	00	00	1.0000
	731				07	B2			0							
	735	4.260045	1.000	ST	07	15 pol.D-Stecker abg.wbl.	0	0	1	0	00	00	00	00	1.0000
	736				07	B1			0							
	740	4.260036	2.000	ST	01	Stereo-Klinkenbuchse 3,5	0	0	1	0	00	00	00	00	2.0000
	741				01	BU4,BU5			0							
	745	4.912008	1.000	ST	07	Blech.Senk.Kreuz. 2,2x13	0	0	1	0	00	00	00	00	1.0000
	750	4.260055	2.000	ST	07	D-Steckerbolzen m.Mutter	0	0	1	0	00	00	00	00	2.0000
	751				07	B1			0							
	755	4.260085	1.000	ST	07	Teststift vergoldet	0	0	1	0	00	00	00	00	1.0000
	760	4.240013	8.000	ST	07	Transistor Montagescheibe	0	0	1	0	00	00	00	00	8.0000
	761				07	T16,T17,T18,T19,T20,T21			0							
	762				07	T22,T23			0							
	765	4.917000	2.000	ST	07	Linsenk.schraube 2,9x6,5	0	0	1	0	00	00	00	00	2.0000

SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba   /0354/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	770	4.260054	1.000	ST	07	15 pol.Kunststoffwinkel	0	0	1	0	00	00	00	00	1.0000
	775	4.910011	2.000	ST	07	Kreuzschlitzschr. M2.5x8	0	0	1	0	00	00	00	00	2.0000
	780	4.920002	2.000	ST	07	Mutter M 2.5 (d=0.5)	0	0	1	0	00	00	00	00	2.0000
	785	4.930029	2.000	ST	07	Fächerscheibe M2.6	0	0	1	0	00	00	00	00	2.0000
	790	4.120311	1.000	ST	01	Sicherungsbez. Kleber	0	0	1	0	00	00	00	00	1.0000
	900				01	--------	0								
	901				01	16.11.88 HP	0								
	902				01	Umstellung DC/DC Wandler	0								
	903				01	auf Ringkern 4.320048	0								
	904				01	Überspannungsableiter	0								
	905				01	entfällt.	0								
	908				01	Umstellung BSS 87 auf	0								
	909				01	IRFS1Z0 T14,T15	0								
	910				01	R153 alt 2k neu 100 Ohm	0								
	911				01	R154 alt 2k neu 100 Ohm	0								
	912				01	R216 alt 150k neu 180k	0								
	997				01	--------	0								
	998				01	Stückliste 3.100 158	0								
	999				01	--------	0								

SCHILLER AG

B A U K A S T E N - S T U E C K L I S T E   Ba /0355/645/25.04.87/

Stufe	Pos.	Artikel-Nr.	Bezeichnung	Gr	Menge	ME	Typ	T	D	F	Nr	S1	S2	S3	Bedarf
		3.100142	MK2-3 Keyboard AT-6			ST	1								1.0000
	001		Stückliste Index -	01					0						
	002		Stand 10.04.87	01					0						
	003			01											
	050	4.490112	AT-6 Keyboard MK2-3	01	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	051			01					0						
	096		Halbleiter	01					0						
	097			01					0						
	100	4.610013	2N2907A	01	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	101		T1	01					0						
	105	4.660013	1N4148	01	8.000	ST	0	0	1	0	00	00	00	00	8.0000
	106		D1,D2,D3,D4,D5,D6,D7,D8	01					0						
	110	4.600023	MV 64B LED grün	01	5.000	ST	0	0	1	0	00	00	00	00	5.0000
	111		D9,D10,D11,D12,D13	01					0						
	195			02											
	196		Widerstände	02					0						
	197			01					0						
	200	4.711102	1K0 1/4W 1%	02	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	201		R18	02					0						
	205	4.722005	4x220 Ohm	02	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	206		R13,R14,R15,R16	02					0						
	210	4.711221	220 OHM 1/4W 1%	02	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	211		R17	02					0						
	295			03					0						
	296		Div. Komponenten	03					0						
	297			03					0						
	300	4.520021	AT-6 Keyboardkabel	03	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	305	4.520022	AT-6 Verbindungsdraht	03	1.000	ST	0	0	1	0	00	00	00	00	1.0000
	898			09											
	899		Änderungen	09					0						
	900		2.4.87 LED Farbe wechselt	09					0						
	901		Alte Artnr 4.600 003 rot	09					0						
	902		Neue Artnr 4.600 023 grün	09					0						
	903			09											

SCHILLER AG

B A U K A S T E N − S T U E C K L I S T E Ba /0355/645/25.04.89/

Stufe / Pos.	Artikel-Nr.	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Menge ME	Bedarf
	3.100143		MK2-4 Backplane AT-6	1								ST	1.0000
001		01	Stückliste Index −				0						
002		01	Stand 10.11.87				0						
003		01					0						
050	4.490114	01	Backplane MK2-4	0	0	1	0	00	00	00	00	1.000 ST	1.0000
051		01					0						
096		01	Widerstände und Potmeter				0						
097		01					0						
100	4.711100	01	10 OHM 1/4W 1%	0	0	1	0	00	00	00	00	1.000 ST	1.0000
101		01	R8				0						
105	4.711102	01	1K0 1/4W 1%	0	0	1	0	00	00	00	00	2.000 ST	2.0000
106		01	R1,R2				0						
110	4.711202	01	2K0 1/4W 1%	0	0	1	0	00	00	00	00	1.000 ST	1.0000
111		01	R5				0						
115	4.711302	01	3K0 1/4W 1%	0	0	1	0	00	00	00	00	1.000 ST	1.0000
116		01	R4				0						
120	4.711103	01	10K 1/4W 1%	0	0	1	0	00	00	00	00	3.000 ST	3.0000
121		01	R3,R6,R9				0						
125	4.711474	01	470K 1/4W 1%	0	0	1	0	00	00	00	00	1.000 ST	1.0000
126		01	R7				0						
130	4.733503	01	Potmeter 50 k stehend	0	0	1	0	00	00	00	00	1.000 ST	1.0000
195		02					0						
196		02	Kondensatoren				0						
197		02					0						
200	4.810102	02	1nF/100V Keramikkond.	0	0	1	0	00	00	00	00	1.000 ST	1.0000
201		02	C1				0						
205	4.820011	02	Elko 100 uF/35V stehend	0	0	1	0	00	00	00	00	1.000 ST	1.0000
206		02	C2				0						
295		03					0						
296		03	Div. Komonenten				0						
297		03					0						
300	4.620047	03	LP 311 N	0	0	1	0	00	00	00	00	1.000 ST	1.0000
301		01	IC1				1						
305	4.260110	03	2 pol. Stiftenleiste geb.	0	0	1	0	00	00	00	00	1.000 ST	1.0000
310	4.260111	03	4 pol. Stiftenleiste geb.	0	0	1	0	00	00	00	00	1.000 ST	1.0000
315	4.261022	03	10-pol. Wanne gebogen	0	0	1	0	00	00	00	00	1.000 ST	1.0000
320	4.260062	03	Federleiste 64 pol. 41612	0	0	1	0	00	00	00	00	4.000 ST	4.0000
325	4.260064	03	Messerleiste 41612 geb.	0	0	1	0	00	00	00	00	1.000 ST	1.0000

Stufe	Pos.	Artikel-Nr.	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf	Menge	ME	Gr
		3.100144	MK2-5 Printer-Timer AT-6	1								1.0000		ST	
	001		Stückliste Index –												01
	002		Stand 10.11.87												01
	003		------												01
	050	4.490113	Timerprint MK2-5	0	0	0	1	00	00	00	00	1.0000	1.000	ST	01
	051		------												01
	096		Halbleiter				0								01
	097		------				0								01
	100	4.645014	74HC393 SMD	0	0	0	1	00	00	00	00	1.0000	1.000	ST	01
	101		U1				0								01
	105	4.645007	74HC138 SMD	0	0	0	1	00	00	00	00	1.0000	1.000	ST	01
	106		U2				0								01
	110	4.645021	74HC123 SMD	0	0	0	1	00	00	00	00	1.0000	1.000	ST	01
	111		U3				0								01
	115	4.645002	74HC04 SMD	0	0	0	1	00	00	00	00	1.0000	1.000	ST	01
	116		U4				0								01
	195		------				0								02
	196		Widerstände und Potmeter				0								02
	197		------				0								02
	200	4.715472	Chip 4,7 k Ohm 2% 1206	0	0	0	1	00	00	00	00	1.0000	1.000	ST	02
	201		R1				0								02
	205	4.715103	Chip 10 k Ohm 2% 1206	0	0	0	1	00	00	00	00	2.0000	2.000	ST	02
	206		R2,R3				0								02
	210	4.715203	Chip 20 k Ohm 2% 1206	0	0	0	1	00	00	00	00	1.0000	1.000	ST	02
	211		R4				0								02
	215	4.732203	Potmeter 20 k liegend	0	0	0	1	00	00	00	00	1.0000	1.000	ST	02
	216		VR2				0								02
	220	4.732503	Potmeter 50 k liegend	0	0	0	1	00	00	00	00	1.0000	1.000	ST	02
	221		VR1				0								02
	295		------				0								03
	296		Kondensatoren				0								03
	297		------				0								03
	300	4.861471	Chip 470 pf 0805	0	0	0	1	00	00	00	00	2.0000	2.000	ST	03
	301		C1,C2				0								03
	305	4.861273	Chip 27 nf 0805	0	0	0	1	00	00	00	00	2.0000	2.000	ST	03
	306		C3,C4				0								03
	310	4.845004	Tantal 68uF/6V	0	0	0	1	00	00	00	00	2.0000	2.000	ST	03
	311		C5,C6				0								03

SCHILLER AG

B A U K A S T E N - S T U E C K L I S T E   Ba   /0355/645/25.04.89/

****

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	315	4.861333	1.000	ST	03	Chip 33 nf 0805	0	0	1	0	00	00	00	00	1.0000
	316				03	C7			0						
	395				04	------------------			0						
	396				04	Div. Komponenten			0						
	397				04	------------------			0						
	405	4.520032	1.000	ST	04	AT-6 Datenkammkabel	0	0	1	0	00	00	00	00	1.0000
	410	4.520033	1.000	ST	04	AT-6 10pol.Interfacekabel	0	0	1	0	00	00	00	00	1.0000

1 SCHILLER AG ████████ B A U K A S T E N - S T U E C K L I S T E Ba /0355/645/25.04.87/

Stufe	Pos.	Artikel-Nr.	Menge ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100145	ST		MK2-6A Powerprint AT-6	1								1.0000
001					Stückliste Index -			0						
002					Stand 19.04.89			0						
003								0						
044		4.490110	1.000 ST	01	AT-6 Powerprint MK2-6A	0	0	1	0	00	00	00	00	1.0000
045				01	Halbleiter			0						
046				01				0						
047				01				0						
050		4.670023	1.000 ST	01	79L15 CP	0	0	1	0	00	00	00	00	1.0000
051				01	U1			0						
055		4.620017	1.000 ST	01	TSC426CPA	0	0	1	0	00	00	00	00	1.0000
056				01	U8			0						
060		4.620021	2.000 ST	01	TSC427CPA	0	0	1	0	00	00	00	00	2.0000
061				01	U2,U8			0						
065		4.670015	3.000 ST	01	UC 3524 AN*	0	0	1	0	00	00	00	00	3.0000
066				01	U3,U9,U12			0						
070		4.625000	2.000 ST	01	TL 062 CD	0	0	1	0	00	00	00	00	2.0000
071				01	U4,U10			0						
075		4.625001	1.000 ST	01	TL064CD	0	0	1	0	00	00	00	00	1.0000
076				01	U5			0						
080		4.620011	1.000 ST	01	L297	0	0	1	0	00	00	00	00	1.0000
081				01	U6			0						
085		4.620012	1.000 ST	01	L298	0	0	1	0	00	00	00	00	1.0000
086				01	U7			0						
090		4.610050	3.000 ST	01	RFP06P08*	0	0	1	0	00	00	00	00	3.0000
091				01	T1,T3,T18			0						
095		4.610052	1.000 ST	01	BUZ71A*	0	0	1	0	00	00	00	00	1.0000
096				01	T8			0						
100		4.615004	1.000 ST	01	MMBT2907A	0	0	1	0	00	00	00	00	1.0000
101				01	T12			0						
105		4.615001	1.000 ST	01	MMBT2222A	0	0	1	0	00	00	00	00	1.0000
106				01	T15			0						
110		4.615002	3.000 ST	01	BC 847 B	0	0	1	0	00	00	00	00	3.0000
111				01	T4,T14,T16			0						
115		4.615003	3.000 ST	01	BC857B	0	0	1	0	00	00	00	00	3.0000
116				01	T5,T13,T17			0						
120		4.610018	1.000 ST	01	TIC116M	0	0	1	0	00	00	00	00	1.0000
121				01	T2			0						

I1 SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba /0355/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	125	4.660007	6.000	ST	01	SB 350	0	0	1	0	00	00	00	00	6.0000
	126				01	D3,D25,GL1 (4x)			0						
	130	4.660016	1.000	ST	01	1N5400	0	0	1	0	00	00	00	00	1.0000
	131				01	D4			0						
	135	4.665002	1.000	ST	01	BAV99	0	0	1	0	00	00	00	00	1.0000
	136				01	D1			0						
	140	4.665003	11.000	ST	01	LL4148F	0	0	1	0	00	00	00	00	11.0000
	141				01	D6,D7,D10,D11,D12,D13,D14			0						
	142				01	D15,D34,D35,D36									
	145	4.665103	1.000	ST	01	BZX84C18	0	0	1	0	00	00	00	00	1.0000
	146				01	D16			0						
	150	4.670002	2.000	ST	01	LM 336 Z 5,0V	0	0	1	0	00	00	00	00	2.0000
	151				01	D8,D9			0						
	155	4.660115	1.000	ST	01	1N5339B (5,6V)	0	0	1	0	00	00	00	00	1.0000
	156				01	D33			0						
	160	4.660012	1.000	ST	01	1N4007	0	0	1	0	00	00	00	00	1.0000
	161				01	D5			0						
	165	4.660005	14.000	ST	01	SB 150	0	0	1	0	00	00	00	00	14.0000
	166				01	D2,D17,D18,D19,D20,D21,			0						
	167				01	D22,D23,D24,D26,D27,D28,			0						
	168				01	D29,D32									
	195				02	--------			0						
	196				02	Widerstände und Potmeter									
	197				02	--------									
	200	4.713024	2.000	ST	01	0,1 Ohm 1% 1W	0	0	1	0	00	00	00	00	2.0000
	201				01	R55,R97			0						
	205	4.713023	1.000	ST	02	0,12 Ohm 1% 1W	0	0	1	0	00	00	00	00	1.0000
	206				02	R19			0						
	210	4.713009	1.000	ST	02	0,15 Ohm 1W	0	0	1	0	00	00	00	00	1.0000
	211				02	R68			0						
	220	4.716109	4.000	ST	02	Melf 1 Ohm 1% 0204	0	0	1	0	00	00	00	00	4.0000
	221				02	R56,R57,R58,R59			0						
	222	4.716180	1.000	ST	01	Melf 18 Ohm 0204	0	0	1	0	00	00	00	00	1.0000
	223				01	R81			0						
	225	4.715270	9.000	ST	01	Chip 27 Ohm 2% 1206	0	0	1	0	00	00	00	00	9.0000
	226				01	R16,R18,R61,R62,R69,R74			0						
	227				01	R89,R90,R98									
	230	4.715221	2.000	ST	02	Chip 220 Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	231				02	R46,R17			0						

1 SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   6a   /0355/645/25.04.87/
****

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	235	4.715561	1.000	ST	02	Chip 560 Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	236				02	R38			0						
	240	4.715102	5.000	ST	02	Chip 1 k Ohm 2% 1206	0	0	1	0	00	00	00	00	5.0000
	241				02	R23,R41,R75,R82,R47			0						
	245	4.716202	7.000	ST	02	Melf 2,0 k Ohm 1% 0204	0	0	1	0	00	00	00	00	7.0000
	246				02	R6,R15,R40,R96,R64			0						
	247				02	R92,R94									
	250	4.715222	1.000	ST	02	Chip 2,2 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	251				02	R10			0						
	255	4.715302	3.000	ST	02	Chip 3 k Ohm 2% 1206	0	0	1	0	00	00	00	00	3.0000
	256				02	R24,R34,R70			0						
	260	4.715332	2.000	ST	02	Chip 3,3 k Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	261				02	R77,R84			0						
	265	4.715432	1.000	ST	02	Chip 4,3 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	266				02	R8			0						
	270	4.715472	1.000	ST	02	Chip 4,7 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	271				02	R26			0						
	275	4.715512	4.000	ST	02	Chip 5,1 k Ohm 2% 1206	0	0	1	0	00	00	00	00	4.0000
	276				02	R3,R21,R60,R88			0						
	280	4.716752	2.000	ST	02	Melf 7,5 k Ohm 1% 0204	0	0	1	0	00	00	00	00	2.0000
	281				02	R12,R65			0						
	285	4.715103	10.000	ST	02	Chip 10 k Ohm 2% 1206	0	0	1	0	00	00	00	00	10.0000
	286				02	R22,R31,R50,R51,R52,R53			0						
	287				02	R54,R76,R83,R87									
	290	4.716113	3.000	ST	02	Melf 11 k Ohm 1% 0204	0	0	1	0	00	00	00	00	3.0000
	291				02	R20,R36,R39			0						
	295	4.716133	2.000	ST	02	Melf 13 k Ohm 1% 0204	0	0	1	0	00	00	00	00	2.0000
	296				02	R43,R67			0						
	300	4.715203	1.000	ST	02	Chip 20 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	301				02	R91			0						
	305	4.715243	3.000	ST	02	Chip 24 k Ohm 2% 1206	0	0	1	0	00	00	00	00	3.0000
	306				02	R35,R80,R86			0						
	310	4.715303	1.000	ST	02	Chip 30 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	311				02	R25			0						
	315	4.715333	4.000	ST	02	Chip 33 k Ohm 2% 1206	0	0	1	0	00	00	00	00	4.0000
	316				02	R5,R42,R63,R79			0						
	320	4.715683	1.000	ST	02	Chip 68 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	321				02	R27			0						
	325	4.716753	2.000	ST	02	Melf 75 k Ohm 1% 0204	0	0	1	0	00	00	00	00	2.0000

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	326				02	R7,R30									
	330	4.715104	2.000	ST	02	Chip 100 k Ohm 2% 1206	0	0	1	0	00	00	00	00	2.0000
	331				02	R4,R49			0						
	335	4.715184	1.000	ST	02	Chip 180 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	336				02	R14			0						
	340	4.715334	4.000	ST	02	Chip 330 k Ohm 2% 1206	0	0	1	0	00	00	00	00	4.0000
	341				02	R29,R93,R95,R28			0						
	345	4.715155	2.000	ST	02	Chip 1,5 M Ohm 5% 1206	0	0	1	0	00	00	00	00	2.0000
	346				02	R13,R37			0						
	350	4.713021	1.000	ST	02	ZNR-Widerstand 390V	0	0	1	0	00	00	00	00	1.0000
	351				02	R1			0						
	352				02	4.713020 ZNR für USA 110v			0						
	355	4.713002	1.000	ST	02	82 Ohm NTC-Widerstand	0	0	1	0	00	00	00	00	1.0000
	356				02	R2			0						
	360	4.713004	1.000	ST	02	1k5 NTC-Widerstand	0	0	1	0	00	00	00	00	1.0000
	361				02	R11			0						
	365	4.732102	1.000	ST	02	Potmeter 1 k liegend	0	0	1	0	00	00	00	00	1.0000
	366				02	R9			0						
	370	4.732202	1.000	ST	02	Potmeter 2 k liegend	0	0	1	0	00	00	00	00	1.0000
	371				02	R48			0						
	375	4.716182	1.000	ST	02	Melf 1,8 k 1% 0204	0	0	1	0	00	00	00	00	1.0000
	376				02	R66			0						
	395				03	───────────────			0						
	396				03	Kondensatoren			0						
	397				03	───────────────			0						
	400	4.861121	2.000	ST	03	Chip 120 pf 0805	0	0	1	0	00	00	00	00	2.0000
	401				03	C12,C76			0						
	405	4.861331	6.000	ST	03	Chip 330 pf 0805	0	0	1	0	00	00	00	00	6.0000
	406				03	C13,C39,C58,C63,C73,C75			0						
	410	4.861681	3.000	ST	03	Chip 680 pf 0805	0	0	1	0	00	00	00	00	3.0000
	411				03	C17,C41,C77			0						
	415	4.861222	1.000	ST	03	Chip 2,2 nF 0805	0	0	1	0	00	00	00	00	1.0000
	416				03	C14			0						
	420	4.861392	1.000	ST	03	Chip 3,9 nF 0805	0	0	1	0	00	00	00	00	1.0000
	421				03	C44			0						
	425	4.861562	1.000	ST	03	Chip 5,6 nF 0805	0	0	1	0	00	00	00	00	1.0000
	426				03	C35			0						
	430	4.861103	5.000	ST	03	Chip 10 nF 0805	0	0	1	0	00	00	00	00	5.0000
	431				03	C7,C23,C33,C38,C80			0						

SCHILLER AG B A U K A S T E N - S T U E C K L I S T E Ba /0355/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Bezeichnung	Gr	Menge ME	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	435	4.861333	Chip 33 nf 0805	03	1.000 ST	0	0	1	0	00	00	00	00	1.0000
	436		C45	03				0						
	440	4.861154	Chip 150 nf	03	27.000 ST	0	0	1	0	00	00	00	00	27.0000
	441		C2,C3,C5,C8,C11,C16,C19	03				0						
	442		C20,C21,C24,C25,C29,C32	03				0						
	443		C37,C42,C48,C81,C84,C40	03				0						
	444		C41,C65,C66,C69,C70,C71	03				0						
	445		C78,C49	03				0						
	450	4.820007	Elko 10 uF/50V stehend	03	14.000 ST	0	0	1	0	00	00	00	00	14.0000
	451		C15,C18,C22,C30,C31,C36	03				0						
	452		C40,C43,C62,C67,C68,C74	03				0						
	453		C79,C28	03				0						
	455	4.820011	Elko 100 uF/35V stehend	03	1.000 ST	0	0	1	0	00	00	00	00	1.0000
	456		C55	03				0						
	460	4.820012	Elko 100 uF/35V stehend	03	1.000 ST	0	0	1	0	00	00	00	00	1.0000
	461		C4	03				0						
	465	4.821004	HF-Elko 470uF/16V stehend	03	12.000 ST	0	0	1	0	00	00	00	00	12.0000
	466		C9,C10,C26,C27,C34,C46	03				0						
	467		C47,C56,C57,C82,C83,C4	03				0						
	470	4.830010	Elko 6800uF/16V axial	03	3.000 ST	0	0	1	0	00	00	00	00	3.0000
	471		C50,C51,C53	03				0						
	475	4.830009	Elko 2200uF/40V axial	03	1.000 ST	0	0	1	0	00	00	00	00	1.0000
	476		C1	03				0						
	495		Induktivitäten	04										
	496			04				0						
	497			04										
	505	4.320030	Ringkern bew. 500 uH	04	1.000 ST	1	0	1	0	00	00	00	00	1.0000
	506		L3	04				0						
	510	4.320029	Lineardrossel 300 uH	04	3.000 ST	0	0	1	0	00	00	00	00	3.0000
	511		L1,L4,L10	04				0						
	515	4.320033	Ringkern bew. 1x38 Wdg	01	2.000 ST	1	0	1	0	00	00	00	00	2.0000
	516		L5,L11	01				0						
	520	4.320046	Drossel 100 uH	04	2.000 ST	0	0	1	0	00	00	00	00	2.0000
	521		L8,L9	04				0						
	525	4.320021	Drossel DL01-24-4,5-0,05	04	1.000 ST	0	0	1	0	00	00	00	00	1.0000
	526		L7	04				0						
	530	4.320045	Breitbanddrossel 1,5 Wdg	04	2.000 ST	0	0	1	0	00	00	00	00	2.0000
	531		L2,L7	04				0						
	535	4.320055	Dämpfungsperle	04	1.000 ST	0	0	1	0	00	00	00	00	1.0000

SCHILLER AG   Ba   /0355/645/25.04.89/

B A U K A S T E N - S T U E C K L I S T E

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	536				04	L12	0								
	595				05		0								
	596				05	Div. Komponenten	0								
	597				05		0								
	600	4.260145	4.000	ST	05	1 pol Stiftenleiste gerad	0	0	1	0	00	00	00	00	4.0000
	605	4.260143	1.000	ST	05	5 pol Stiftenleiste gerad	0	0	1	0	00	00	00	00	1.0000
	610	4.260076	16.000	ST	05	Steckzunge 2,8/0,8 mm	0	0	1	0	00	00	00	00	16.0000
	615	4.260062	1.000	ST	05	Federleiste 64 pol. 41612	0	0	1	0	00	00	00	00	1.0000
	620	4.260026	2.000	ST	05	Molex Buchse	0	0	1	0	00	00	00	00	2.0000
	625	4.260028	1.000	ST	05	2 pol. Buchsenhalter	0	0	1	0	00	00	00	00	1.0000
	630	4.210050	1.000	ST	05	Sicherungshalter 031.8001	0	0	1	0	00	00	00	00	1.0000
	635	4.210009	1.000	ST	05	Sicherung 1,25 AF	0	0	1	0	00	00	00	00	1.0000
	640	4.240000	4.000	ST	05	Kühlkörper PR 17/15	0	0	1	0	00	00	00	00	4.0000
	641				05	T1,T3,T8,T18	0								
	645	4.910011	4.000	ST	05	Kreuzschlitzschr. M2.5x8	0	0	1	0	00	00	00	00	4.0000
	650	4.920002	4.000	ST	05	Mutter M 2,5 (d=0,5)	0	0	1	0	00	00	00	00	4.0000
	655	4.530007	5.000	ST	01	Kabelbinder 100 mm	0	0	1	0	00	00	00	00	5.0000
	660	4.930029	4.000	ST	01	Fächerscheibe M2,6	0	0	1	0	00	00	00	00	4.0000
	665	4.530004	0.020	M	01	Schrumpfschl. 12mm sw	0	0	1	0	00	00	00	00	0.0200
	900				09		0								
	901				09	Änderungen + Bemerkungen	0								
	902				09		0								
	903				09	13.04.87 (RS)	0								
	904				09	R66 alt 2k, neu 1k8	0								
	905				09		0								
	906				09	29.07.87	0								
	907				09	C1 2200uF/40V Nachtrag	0								
	908				09	Fächerscheiben M2,6	0								
	909				09		0								
	910				09	04.01.88 (KO)	0								
	911				09	Umstellung Lager 75k neu	0								
	912				09	Melf 1%	0								
	913				09		0								
	914				01	13.01.1989 BM	0								
	915				01	R81 alt 27 Ohm neu 18 Ohm	0								
	916				01		0								
	917				01	19.04.89 BM	0								
	918				01	Anpassung an SP-300	0								
	919				01	R97 alt 0,22 neu 0,1 Ohm	0								

SCHILLER AG   B A U K A S T E N - S T U E C K L I S T E   Ba /0355/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T D P Nr	S1	S2	S3	Bedarf
		920			01	L11 alt 800uH neu 100uH		0				
		921			01	------------------------		0				

J1 SCHILLER AG   KO   /0375/645/25.04.89/

BAUKASTEN-STUECKLISTE

Stufe	Pos.	Artikel-Nr.	Bezeichnung	Menge	ME	Gr	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100220	MK 2-92 Spiro stand-alone		ST		1								1.0000
	001		Stückliste Index -			01		0							
	002		Stand 14.12.88			01		0							
	003					01		0							
	050	4.490159	Print MK2-92	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	097					01		0							
	098		Halbleiter			01		0							
	099					01		0							
	100	4.640011	74HC259	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	101		U1			01		0							
	105	4.650031	PAL SCHILLER 002	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	106		U2			01		0							
	110	4.640022	74HC257	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	111		U3			01		0							
	177					01		0							
	198		Widerstände			01		0							
	199					01		0							
	200	4.711103	10K 1/4W 1%	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	201		R1			01		0							
	297					01		0							
	298		Kondensatoren			01		0							
	299					01		0							
	300	4.830003	Elko 220uF/16V axial	3.000	ST	01	0	0	1	00	00	00	00		3.0000
	301		C1,C2,C3			01		0							
	305	4.812080	100nF/63V/10% Vielschicht	5.000	ST	01	0	0	1	00	00	00	00		5.0000
	306		C4,C5,C6,C7,C8			01		0							
	397					01		0							
	398		Div. Komponenten			01		0							
	399					01		0							
	400	4.260064	Messerleiste 41612 geb.	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	405	4.260191	D-Stecker 25p abgw wb kpt	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	420	4.910007	Kreuzschlitzschr. M3x8	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	425	4.920003	Mutter M3 (d=0,5)	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	430	4.930030	Fächerscheibe M3	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	435	4.917000	Linsenk.schraube 2,9x6,5	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	436		für Stecker ST1			01		0							

74 SCHILLER AG B A U K A S T E N - S T U E C K L I S T E KO /0374/645/25.04.89/

****

Stufe	Pos.	Artikel-Nr.	Bezeichnung	Menge	ME	Gr	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100217	MKZ-91 (RS, Spiro)		ST		1								1.0000
	001		Stückliste Index —			01									
	002		Stand 03.12.88			01									
	003					01									
	050	4.490107	Print MK 2-91	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	097		Halbleiter			01									
	098					01									
	099					01									
	100	4.645011	74HC257 SMD	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	101		U16			01									
	105	4.650042	EXO 3C 19.6608 MHz	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	106		U14			01									
	110	4.645012	74HC259 SMD	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	111		U15			01									
	115	4.650031	PAL SCHILLER 002	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	116		U17			01									
	120	4.655017	MB 89371 GFP	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	121		U18			01									
	125	4.635016	MC 145406 DW	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	126		U19,U20			01									
	197		Kondensatoren			01									
	198					01									
	199					01									
	200	4.825003	Elko 47uF/16V SMD	2.000	ST	01	0	0	1	00	00	00	00		2.0000
	201		C1,C3			01									
	205	4.825005	Elko 100uF/6.3V SMD	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	206		C2			01									
	210	4.861473	Chip 47 nf 0805	8.000	ST	01	0	0	1	00	00	00	00		8.0000
	211		C4,C5,C6,C9,C16,C17,C25			01									
	212		C26			01									
	297		Widerstände			01									
	298					01									
	299					01									
	300	4.715103	Chip 10 k Ohm 2% 1206	1.000	ST	01	0	0	1	00	00	00	00		1.0000
	301		R3			01									
	397		Div. Komponenten			01									
	398					01									
	399					01									

31 SCHILLER AG

B A U K A S T E N - S T U E C K L I S T E   KO   /0374/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	400	4.260055	2.000	ST	01	D-Steckerbolzen m.Mutter	0	0	1	0	00	00	00	00	2.0000
	405	4.260064	1.000	ST	01	Messerleiste 41612 geb.	0	0	1	0	00	00	00	00	1.0000
	406				01	ST1			0						
	415	4.260046	1.000	ST	01	25.pol.D-Stecker abgw.wb.	0	0	1	0	00	00	00	00	1.0000
	416				01	ST3			0						
	420	4.260052	1.000	ST	01	25 pol. Kunststoffwinkel	0	0	1	0	00	00	00	00	1.0000
	425	4.910007	2.000	ST	01	Kreuzschlitzschr. M3x8	0	0	1	0	00	00	00	00	2.0000
	430	4.920003	2.000	ST	01	Mutter M3 (d=0,5)	0	0	1	0	00	00	00	00	2.0000
	435	4.930030	2.000	ST	01	Fächerscheibe M3	0	0	1	0	00	00	00	00	2.0000
	440	4.917000	2.000	ST	01	Linsenk.schraube 2,9x6,5	0	0	1	0	00	00	00	00	2.0000
	441				01	für ST1			0						
	465	4.430054	1.000	ST	01	Distanzsäule 12mm 1i/1a	0	0	1	0	00	00	00	00	1.0000

21 SCHILLER AG B A U K A S T E N - S T U E C K L I S T E KO /0374/645/25.04.87/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
		3.100216		ST		MK2-91 (Video RS Spiro)	1								1.0000
	001				01	Stückliste Index -			0	0	00				
	002				01	Stand 03.12.1988			0	0	00				
	003				01										
	050	4.490107	1.000	ST	01	Print MK 2-91	0	0	1	0	00	00	00	00	1.0000
	097				01				0	0	00				
	078				01	Halbleiter			0	0	00				
	099				01				0	0	00				
	100	4.650025	1.000	ST	01	HD 63484UP-8	0	0	1	0	00	00	00	00	1.0000
	101				01	U1									
	105	4.650030	1.000	ST	01	PAL SCHILLER 001	0	0	1	0	00	00	00	00	1.0000
	106				01	U2									
	110	4.645022	1.000	ST	01	74HC564 SMD	0	0	1	0	00	00	00	00	1.0000
	111				01	U3									
	115	4.645011	3.000	ST	01	74HC257 SMD	0	0	1	0	00	00	00	00	3.0000
	116				01	U4,U5,U16									
	120	4.655005	4.000	ST	01	TMS4464-15FML	0	0	1	0	00	00	00	00	4.0000
	121				01	U6,U7,U8,U9									
	125	4.645019	2.000	ST	01	74HC166 SMD	0	0	1	0	00	00	00	00	2.0000
	126				01	U10,U11									
	130	4.645050	2.000	ST	01	74AC04 SMD	0	0	1	0	00	00	00	00	2.0000
	131				01	U12,U13									
	135	4.650042	1.000	ST	01	EXO 3C 19,6608 MHz	0	0	1	0	00	00	00	00	1.0000
	136				01	U14			0						
	140	4.645012	1.000	ST	01	74HC259 SMD	0	0	1	0	00	00	00	00	1.0000
	141				01	U15									
	145	4.650031	1.000	ST	01	PAL SCHILLER 002	0	0	1	0	00	00	00	00	1.0000
	146				01	U17									
	150	4.655017	1.000	ST	01	MB 89371 QFP	0	0	1	0	00	00	00	00	1.0000
	151				01	U18									
	155	4.635016	2.000	ST	01	MC 145406 DW	0	0	1	0	00	00	00	00	2.0000
	156				01	U19,U20									
	197				01				0	0					
	198				01	Kondensatoren			0	0					
	199				01										
	200	4.825003	2.000	ST	01	Elko 47uF/16V SMD	0	0	1	0	00	00	00	00	2.0000
	201				01	C1,C3									
	205	4.825005	1.000	ST	01	Elko 100uF/6,3V SMD	0	0	1	0	00	00	00	00	1.0000

DI SCHILLER AG · · · · · · · · · · · · · · · · · B A U K A S T E N - S T U E C K L I S T E · · · · · · · KO /0374/645/25.04.89/

Stufe	Pos.	Artikel-Nr.	Menge	ME	Gr	Bezeichnung	Typ	T	D	P	Nr	S1	S2	S3	Bedarf
	206				01	C2			0						
	210	4.861473	22.000	ST	01	Chip 47 nf 0805	0	0	1	0	00	00	00	00	22.0000
	211				01	C4,C5,C6,C9,C10,C11,C12			0						
	212				01	C13,C14,C15,C16,C17,C18			0						
	213				01	C19,C20,C21,C22,C23,C24			0						
	214				01	C25,C26,C27			0						
	215	4.861470	1.000	ST	01	Chip 47 pF 0805	0	0	1	0	00	00	00	00	1.0000
	216				01	C8			0						
	220	4.861330	1.000	ST	01	Chip 33 pf 0805	0	0	1	0	00	00	00	00	1.0000
	221				01	C7			0						
	297				01	Widerstände			0						
	298				01	----------------------									
	299				01	----------------------									
	300	4.715102	1.000	ST	01	Chip 1 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	301				01	R1			0						
	305	4.715221	1.000	ST	01	Chip 220 Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	306				01	R2			0						
	310	4.715103	1.000	ST	01	Chip 10 k Ohm 2% 1206	0	0	1	0	00	00	00	00	1.0000
	311				01	R3			0						
	397				01	----------------------									
	398				01	Div. Komponenten			0						
	399				01	----------------------									
	400	4.260055	2.000	ST	01	D-Steckerbolzen m.Mutter	0	0	1	0	00	00	00	00	2.0000
	405	4.260064	1.000	ST	01	Messerleiste 41612 geb.	0	0	1	0	00	00	00	00	1.0000
	406				01	ST1			0						
	410	4.260070	1.000	ST	01	9 pol. D-Stecker abg.weib	0	0	1	0	00	00	00	00	1.0000
	411				01	ST2			0						
	415	4.260191	1.000	ST	01	D-Stecker 25p abgw wb kpt	0	0	1	0	00	00	00	00	1.0000
	416				01	ST3			0						
	420	4.260071	1.000	ST	01	9 pol.Kunststoffwinkel	0	0	1	0	00	00	00	00	1.0000
	435	4.910007	4.000	ST	01	Kreuzschlitzschr. M3x8	0	0	1	0	00	00	00	00	4.0000
	440	4.920003	4.000	ST	01	Mutter M3 (d=0,5)	0	0	1	0	00	00	00	00	4.0000
	445	4.930030	4.000	ST	01	Fächerscheibe M3	0	0	1	0	00	00	00	00	4.0000
	450	4.250009	1.000	ST	01	IC-Sockel 64 pol.	0	0	1	0	00	00	00	00	1.0000
	455	4.917000	2.000	ST	01	Linsenk.schraube 2,9x6,5	0	0	1	0	00	00	00	00	2.0000
	460	4.530010	1.000	ST	01	Kabelbinder 300 mm	0	0	1	0	00	00	00	00	1.0000
	465	4.430054	1.000	ST	01	Distanzsäule 12mm 1i/1a	0	0	1	0	00	00	00	00	1.0000

Proposed Spares for CARDIOVIT AT-6

|		
AT-6 μPCB	3.100225	(NON-EXEC, Standard)
AT-6 μPCB	3.100230	(EXEC, Std.)
SP-200 μPCB ?	3.100229	(Spirometry μPcb)
ECG amplifier	3.100260	
Power supply PCB	3.100145	
AT-6 Spiro stand-alone	3.100220	(Extension Pcb)
AT-6 Spiro/RS-232	3.100217	(Extension Pcb)
AT-6 Spiro/RS-232/Vid	3.100216	(Extension Pcb)
AT-6 Keyboard	3.100142	(complete assy.)
Lead Acid accumulator	4.350005	
240 Vac power transf.	4.320084	(240 Vac type)
AT-6 LCD display	3.900516	(not compat. with AT-3 LCD !)
LCD Plexi-prot.cover	4.435003	
Paper breaking edge	4.415013	(anodized edge plate)
Paper drive cylinder	4.410018	(complete assy.)
Paper drive bearing	4.410041	(2/unit)
Paper table	3.900500	(complete assy.)
Side mask plate	4.450023	(AT-6 standard side plate)
Side mask plate	4.450025	(With RS-232/Spiro orifice)
Side mask plate	4.450032	(SP-200 & RS-232)

? =   depending on need and number of units sold

SECTION 10

CIRCUIT UPDATE INFORMATION

Drawing No.

Cable Tester   1200201

TEST

BU8

R212 30k
C123 390pF
9 10 8 IC9 TL064
C121 100nF
1N914 D16
R213 1.1k
C124 3.3nF
R214 3.3M
R215 10k
+5Vi +5Vi
R216 150k
6 5 4 7 IC9 11 TL064
R217 1.1k
LED1
-5Vi
-9Vi

R218 47k
R219 47k
T12 BC847
R220 10k
-9Vi
C127 1uF
D2 1.25V MPS010
-9Vi -9Vi

BAV99 D22
C120 100nF
R221 30k
-9Vi -9Vi
14 IC9 TL064 12 13
R222 150k
R223 150k
R225 1.5M
-9Vi
150k R224
C122 3.9nF